

TECHNICAL REPORT

**Fibre optic communication system design guidelines –
Part 16: Coherent receivers and transmitters with high-speed digital signal
processing**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2022 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

Preview generated by EVS

TECHNICAL REPORT

**Fibre optic communication system design guidelines –
Part 16: Coherent receivers and transmitters with high-speed digital signal
processing**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.01

ISBN 978-2-8322-0094-0

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

| | |
|---|----|
| FOREWORD..... | 6 |
| INTRODUCTION..... | 8 |
| 1 Scope..... | 9 |
| 2 Normative references | 9 |
| 3 Terms, definitions, and abbreviated terms | 9 |
| 3.1 Terms and definitions..... | 9 |
| 3.2 Abbreviated terms..... | 9 |
| 4 Background | 12 |
| 5 Coherent transmission of vector-modulated signals | 13 |
| 5.1 Typical receiver architecture | 13 |
| 5.2 Typical transmitter architecture | 14 |
| 5.3 Vector-modulated signals..... | 15 |
| 5.3.1 Mathematical description | 15 |
| 5.3.2 Binary amplitude and phase modulation..... | 16 |
| 5.3.3 Quadrature amplitude modulation | 17 |
| 5.3.4 Polarization multiplexing | 18 |
| 5.3.5 Higher-dimensional coding and constellation shaping | 18 |
| 6 Coherent receiver architectures and functional capabilities..... | 19 |
| 6.1 Basic principle of coherent detection..... | 19 |
| 6.1.1 General | 19 |
| 6.1.2 Homodyne and heterodyne detection..... | 19 |
| 6.1.3 Intradyne detection | 21 |
| 6.1.4 Polarization dependence | 21 |
| 6.1.5 Frequency dependence | 22 |
| 6.1.6 Phase and polarization diversity | 22 |
| 6.2 Single coherent mixer with balanced detection..... | 23 |
| 6.2.1 Principle of operation..... | 23 |
| 6.2.2 Common-mode rejection | 24 |
| 6.2.3 Polarization dependence | 26 |
| 6.2.4 Homodyne detection | 27 |
| 6.2.5 Heterodyne detection..... | 28 |
| 6.3 Dual coherent mixer with phase diversity | 29 |
| 6.3.1 Principle of operation..... | 29 |
| 6.3.2 Intradyne detection with frequency offset removal..... | 31 |
| 6.3.3 Compensation of chromatic dispersion..... | 33 |
| 6.3.4 Compensation of I - Q skew and phase offset | 40 |
| 6.3.5 Spectral shaping and frequency equalization | 42 |
| 6.4 Quadruple mixer with phase and polarization diversity | 46 |
| 6.4.1 Principle of operation..... | 46 |
| 6.4.2 Polarization demultiplexing | 48 |
| 6.4.3 Compensation of polarization-mode dispersion | 51 |
| 6.4.4 Compensation of polarization-dependent loss and residual CD | 53 |
| 6.4.5 Carrier phase recovery | 54 |
| 6.4.6 Impact of laser phase noise | 55 |
| 6.5 High-resolution spectral analysis with coherent receivers..... | 62 |
| 6.5.1 Measurement methods | 62 |

| | | |
|--------|---|-----|
| 6.5.2 | Dual mixer with polarization diversity | 63 |
| 6.5.3 | Examples of high-resolution spectral analysis | 64 |
| 7 | Digital signal processing in coherent receivers | 66 |
| 7.1 | Basic features of digital signal processing | 66 |
| 7.2 | Real-time DSPs for fibre optic communication systems | 70 |
| 7.2.1 | Basic functions | 70 |
| 7.2.2 | Timing recovery | 71 |
| 7.2.3 | Cycle slip detection | 71 |
| 7.2.4 | Compensation of nonlinear transmission effects | 71 |
| 7.2.5 | FEC decoding and performance monitoring | 72 |
| 7.3 | Software-based DSPs for optical modulation analysers | 73 |
| 8 | Transmitters for vector-modulated signals | 75 |
| 8.1 | Generation of vector-modulated signals | 75 |
| 8.2 | Single Mach-Zehnder modulator | 77 |
| 8.2.1 | Principle of operation | 77 |
| 8.2.2 | Modulator extinction ratio | 81 |
| 8.2.3 | Adaptive bias control in Mach-Zehnder modulators | 83 |
| 8.3 | Dual Mach-Zehnder modulators | 85 |
| 8.3.1 | Quadrature-amplitude modulation | 85 |
| 8.3.2 | Compensation of finite extinction ratio | 86 |
| 8.3.3 | Adaptive control of I - Q phase | 87 |
| 8.4 | Quadruple modulators for polarization-multiplexed signals | 91 |
| 9 | Digital signal processing in transmitters for vector-modulated signals | 94 |
| 9.1 | Pre-distortion of optical signals | 94 |
| 9.1.1 | General | 94 |
| 9.1.2 | Pre-compensation of linear transmitter impairments | 95 |
| 9.1.3 | Determination of transmitter frequency response | 96 |
| 9.1.4 | Determination of transmitter skew | 101 |
| 9.1.5 | Pre-compensation of modulator nonlinearity | 103 |
| 9.2 | Symbol mapper, FEC encoding and framing | 105 |
| 10 | Implementation and typical performance specifications | 106 |
| 10.1 | Coherent receiver | 106 |
| 10.1.1 | Implementation | 106 |
| 10.1.2 | Typical performance specifications | 107 |
| 10.2 | Optical transmitter | 108 |
| 10.2.1 | Implementation | 108 |
| 10.2.2 | Typical performance specifications | 109 |
| 10.3 | Integrated coherent receiver and transmitter | 111 |
| 10.4 | Tuneable laser assemblies | 111 |
| 10.4.1 | Implementation | 111 |
| 10.4.2 | Typical performance specifications | 111 |
| | Bibliography | 113 |
| | Figure 1 – Coherent optical receiver | 13 |
| | Figure 2 – Optical transmitter for coherent transmission | 14 |
| | Figure 3 – Generation of vector modulated signals | 16 |
| | Figure 4 – Examples of modulation formats for coherent communication | 17 |
| | Figure 5 – Signal and local oscillator frequencies for homodyne detection | 20 |

| | |
|---|----|
| Figure 6 – Signal and local oscillator frequencies for heterodyne detection | 20 |
| Figure 7 – Electrical spectra of homodyne and heterodyne beat signals | 21 |
| Figure 8 – Single balanced mixer for coherent reception | 24 |
| Figure 9 – Balanced heterodyne mixer with electrical down-mixing | 28 |
| Figure 10 – Dual coherent mixer with phase diversity | 30 |
| Figure 11 – Intradyne beat spectrum with 2 GHz frequency offset | 32 |
| Figure 12 – Differential phase shifts introduced by 3 000 ps/nm GVD | 33 |
| Figure 13 – Transfer function for GVD of 3 ns/nm in frequency domain | 34 |
| Figure 14 – Inverse transfer functions for GVD of 3 ns/nm and 10 ns/nm in time domain | 36 |
| Figure 15 – Fractionally spaced equalizer with a tapped delay line | 37 |
| Figure 16 – Processing steps for CD compensation in the frequency domain | 38 |
| Figure 17 – Data processing for CD compensation in the frequency domain | 39 |
| Figure 18 – Dual coherent mixer with optical phase offset and signal skew | 40 |
| Figure 19 – Skew and phase offset removal in a DSP | 41 |
| Figure 20 – Example of an I - Q skew and phase error measurement | 42 |
| Figure 21 – Fifth-order Bessel filter emulated with a 5-tap FSE | 43 |
| Figure 22 – Shape of inverse Bessel filter generated with a 9-tap FSE | 44 |
| Figure 23 – Amplitude and phase of FSE-generated inverse Bessel filter | 45 |
| Figure 24 – Root-raised-cosine filter emulated with a 33-tap FSE | 46 |
| Figure 25 – Quadruple coherent mixer with phase and polarization diversity | 47 |
| Figure 26 – 2×2 matrix operation for adaptive polarization demultiplexing | 49 |
| Figure 27 – Constellation points of QPSK signal after polarization demultiplexing | 50 |
| Figure 28 – 16QAM signal before and after polarization demultiplexing | 50 |
| Figure 29 – FSE-based compensator for polarization-mode dispersion | 52 |
| Figure 30 – QPSK signal constellations for various amounts of PMD | 52 |
| Figure 31 – QPSK signal constellations for various amounts of PDL | 53 |
| Figure 32 – QPSK signal constellations for various amounts of GVD | 53 |
| Figure 33 – Optical phase noise of two narrow-linewidth lasers | 56 |
| Figure 34 – Optical frequency noise spectra of two lasers | 58 |
| Figure 35 – Optical phase noise spectra of two lasers | 59 |
| Figure 36 – Laser phase noise measurement with optical bandpass filter | 60 |
| Figure 37 – Dual coherent mixer with polarization diversity | 63 |
| Figure 38 – High-resolution optical spectrum of a 32 GBd QPSK signal | 65 |
| Figure 39 – QPSK signal measured with coherent OSA and with grating-based OSA | 65 |
| Figure 40 – Typical digital signal processing steps in a coherent receiver | 67 |
| Figure 41 – 100 Gbit/s PM-QPSK signal before and after fibre transmission | 68 |
| Figure 42 – De-convolution of a 100 Gbit/s PM-QPSK signal at various DSP stages | 69 |
| Figure 43 – Block diagram of specially designed integrated circuit with DSP | 70 |
| Figure 44 – Block diagram of OMA with software-based DSP | 73 |
| Figure 45 – Typical arrangement for generation of vector-modulated signals | 76 |
| Figure 46 – Differentially driven Mach-Zehnder modulator | 77 |
| Figure 47 – Mach-Zehnder modulator with adaptive bias control | 78 |
| Figure 48 – MZM operation for intensity modulation | 79 |

| | |
|---|-----|
| Figure 49 – Nonlinear MZM operation for binary PSK/ASK..... | 80 |
| Figure 50 – Linear MZM operation for quaternary ASK signals..... | 81 |
| Figure 51 – Optical power variations in an NRZ-OOK signal with finite extinction ratio..... | 82 |
| Figure 52 – Optical and RF output power versus bias voltage for linear operation..... | 83 |
| Figure 53 – Dual MZM with adaptive I - Q phase control | 86 |
| Figure 54 – RF output power of I - Q modulator versus I - Q phase..... | 88 |
| Figure 55 – Error signal for I - Q phase control derived from MZM bias dither | 90 |
| Figure 56 – I - Q phase error resulting from offset in feedback signal..... | 91 |
| Figure 57 – Dual I - Q modulators for polarization multiplexing..... | 92 |
| Figure 58 – Adaptive bias and phase control in dual-polarization I - Q modulator..... | 93 |
| Figure 59 – Typical digital signal processing steps in the transmitter | 95 |
| Figure 60 – Spectrum and samples of a white test vector..... | 96 |
| Figure 61 – Magnitude of transmitter frequency response | 97 |
| Figure 62 – Phase of transmitter frequency response | 98 |
| Figure 63 – Example of magnitude and phase of a pre-compensation filter | 99 |
| Figure 64 – Tap coefficients and effect of a 9-tap pre-compensation filter..... | 99 |
| Figure 65 – Impact of pre-compensation on signal waveform in DSP and DAC | 101 |
| Figure 66 – I - Q skew in a single-sideband modulated signal | 102 |
| Figure 67 – Non-linear pre-distortion of a Mach-Zehnder modulator..... | 103 |
| Figure 68 – Linearized MZM operation for quaternary ASK | 105 |
| Table 1 – Typical receiver specifications..... | 108 |
| Table 2 – Typical modulator specifications..... | 110 |
| Table 3 – Additional specifications for integrated driver-modulator..... | 110 |
| Table 4 – Typical specifications for tuneable laser assemblies..... | 112 |

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –**Part 16: Coherent receivers and transmitters
with high-speed digital signal processing****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61282-16 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics. It is a Technical Report.

The text of this Technical Report is based on the following documents:

| | |
|--------------|------------------|
| Draft | Report on voting |
| 86C/1776/DTR | 86C/1782/RVDTR |

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Report is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61282 series, published under the general title *Fibre optic communication system design guidelines*, can be found on the IEC website.

Future documents in this series will carry the new general title as cited above. Titles of existing documents in this series will be updated at the time of the next edition.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

Coherent optical receivers are widely used in long-haul fibre optic communication systems, especially in systems that transmit optical carriers at data rates of 100 Gbit/s and higher. While the principle of coherent detection is very similar to that of super-heterodyne (or homodyne) detection in radio and microwave receivers, its implementation is significantly more challenging. The main reason is that optical frequencies are substantially higher than radio frequencies, so it becomes more difficult to match the local oscillator frequency in the coherent receiver to the frequency of the transmitted optical signal. Furthermore, optical signals tend to be highly polarized, which means that the amplitude of a coherently received signal can be substantially reduced or even vanish if the polarization state of the local oscillator light does not match the polarization state of the received optical signal. This polarization matching is particularly difficult to achieve in fibre optic communications systems, which usually do not preserve the launched state of polarization of the transmitted signal. To overcome these problems, modern coherent receivers typically consist of four parallel coherent optical mixers that provide phase and polarization diversity, and they rely on high-speed digital signal processors to retrieve the transmitted data from the four received electrical signals.

This rather complex coherent receiver architecture is further justified by the fact that it allows the receiver to mitigate various types of signal impairments introduced in the fibre optic link (or in the receiver itself) simply by means of additional electronic signal processing. Most notably, it is possible to substantially reduce the signal distortions caused by polarization-mode dispersion (PMD) or uncompensated chromatic dispersion (CD) in the fibre link, without requiring additional optical PMD or CD compensators. For this reason, coherent optical communication systems generally allow signal transmission at much higher data rates than communication systems using direct-detection receivers. Furthermore, coherent detection with subsequent digital signal processing facilitates the decoding of complex vector-modulated signals, such as quadrature-amplitude modulated signals (QAM) and polarization-multiplexed (PM) signals, and thereby the transmission of higher data rates.

Aside from fibre optic communications systems, coherent optical receivers are also used in various test and measurement instrumentation. Most notable examples are optical modulation analysers (OMAs) and high-resolution optical spectrum analysers (HR-OSAs). Optical modulation analysers are high-performance optical reference receivers and are used to assess the signal quality of complex vector-modulated optical signals. They are typically composed of a carefully calibrated coherent receiver and a high-speed real-time digitizing oscilloscope to record the coherently received signals, which are then analysed with the help of a software-based digital signal processor.

High-resolution optical spectrum analysers are often used to analyse narrowband features of the optical spectrum of a modulated signal, such as a residual optical carrier or other spectral lines. In contrast to OMAs, they typically employ a low-speed coherent receiver, so as to utilize the frequency-selectivity of coherent detection. The key component in these instruments is a continuously tuneable local oscillator, which is scanned over the frequency range of the signal to be analysed while the total power of the coherently received signal is recorded. The spectral resolution of these instruments can be of the order of a few MHz. Other examples of coherent optical test instruments include in-service PMD analysers and in-band optical signal-to-noise ratio analysers for polarization-multiplexed signals.

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 16: Coherent receivers and transmitters with high-speed digital signal processing

1 Scope

This part of IEC 61282 is a technical report on coherent optical receiver and transmitter technologies that are employed in fibre optic communication systems as well as in optical test and measurement equipment. This document describes the principle of operation and functional capabilities of coherent optical receivers as well as the operation of optical transmitters used to generate complex vector-modulated signals. It is intended to serve as a technical foundation for other IEC documents and standards related to coherent optical transmission techniques.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-731, *International Electrotechnical Vocabulary (IEV) – Part 731: Optical fibre communication* (available at www.electropedia.org)

IEC TR 61931, *Fibre optic – Terminology*

3 Terms, definitions, and abbreviated terms

3.1 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-731 and IEC TR 61931 apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.2 Abbreviated terms

| | |
|------|---|
| ABC | adaptive bias control |
| ADC | analogue-to-digital converter |
| AM | amplitude modulation |
| ASIC | application-specific integrated circuit |
| ASK | amplitude-shift keying |
| BER | bit-error ratio |
| BPSK | binary phase-shift keying |
| CD | chromatic dispersion |
| CFP | C form-factor pluggable |
| CMA | constant modulus algorithm |