

INTERNATIONAL STANDARD

NORME INTERNATIONALE



General requirements for arc fault detection devices

Exigences générales des dispositifs pour la détection de défaut d'arcs



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2013 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

Useful links:

IEC publications search - www.iec.ch/searchpub

The advanced search enables you to find IEC publications by a variety of criteria (reference number, text, technical committee,...).

It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available on-line and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary (IEV) on-line.

Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Liens utiles:

Recherche de publications CEI - www.iec.ch/searchpub

La recherche avancée vous permet de trouver des publications CEI en utilisant différents critères (numéro de référence, texte, comité d'études,...).

Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

Just Published CEI - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications de la CEI. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (VEI) en ligne.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



General requirements for arc fault detection devices

Exigences générales des dispositifs pour la détection de défaut d'arcs

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

XH

ICS 29.120; 29.120.50

ISBN 978-2-8322-0900-4

Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

CONTENTS

FOREWORD.....	9
INTRODUCTION.....	11
1 Scope.....	12
2 Normative references	13
3 Terms and definitions	14
4 Classification.....	17
4.1 According to the method of construction	17
4.2 According to the method of mounting and connection	17
4.3 According to the number of poles and current paths	17
4.4 AFDD providing monitoring information	17
5 Characteristics of AFDDs	17
5.1 Summary of characteristics and conditions to mitigate the risk of fire	17
5.2 Rated quantities and other characteristics	18
5.2.1 Rated voltage	18
5.2.2 Rated current (I_n)	18
5.2.3 Rated frequency	18
5.2.4 Rated making and breaking capacity (I_m)	18
5.2.5 Rated making and breaking capacity on one pole (I_{m1})	19
5.3 Standard and preferred values	19
5.3.1 Preferred values of rated voltage (U_n)	19
5.3.2 Preferred values of rated current (I_n)	19
5.3.3 Preferred values of rated frequency	19
5.3.4 Minimum value of the rated making and breaking capacity (I_m)	19
5.3.5 Minimum value of the rated making and breaking capacity on one pole (I_{m1})	19
5.3.6 Standard and preferred values of the rated conditional short-circuit current (I_{nc}) and standard and preferred values of the rated conditional short circuit current for one pole (I_{nc1})	19
5.3.7 Limiting values of operating criteria for AFDDs for low and high arc currents	20
5.4 Standard value of rated impulse withstand voltage (U_{imp})	21
5.5 Coordination with short-circuit protective devices (SCPDs)	21
5.5.1 General	21
5.5.2 Rated conditional short-circuit current (I_{nc}) and rated conditional short-circuit on one pole (I_{nc1})	21
5.5.3 Operating characteristics of opening means for AFDDs according to 4.1.1	21
6 Marking and other product information.....	22
6.1 Marking	22
6.2 Additional marking for AFDDs according to 4.1.1	24
6.2.1 Marking of AFDDs	24
6.2.2 Instructions for wiring and operation	24
7 Standard conditions for operation in service and for installation.....	25
7.1 Standard conditions.....	25
7.2 Conditions of installation	25
7.3 Pollution degree	25
8 Requirements for construction and operation.....	26

8.1	General	26
8.2	Mechanical design.....	26
8.2.1	General	26
8.2.2	Mechanism	27
8.2.3	Clearances and creepage distances (see Annex B)	28
8.2.4	Screws, current-carrying parts and connections.....	31
8.2.5	Terminals for external conductors	31
8.3	Protection against electric shock	33
8.4	Dielectric properties and isolating capability	34
8.5	Temperature rise	34
8.5.1	Temperature-rise limits	34
8.5.2	Ambient air temperature	35
8.6	Operating characteristics.....	35
8.6.1	Operating characteristics of the protective device part.....	35
8.6.2	Operating characteristics	35
8.7	Mechanical and electrical endurance	36
8.8	Performance at short-circuits currents	36
8.9	Resistance to mechanical shock and impact.....	36
8.10	Resistance to heat.....	36
8.11	Resistance to abnormal heat and to fire	36
8.12	Behaviour of AFDDs in case of overcurrents in the main circuit	36
8.13	Behaviour of AFDDs in case of current surges caused by impulse voltages.....	37
8.14	Reliability	37
8.15	Electromagnetic compatibility (EMC)	37
8.16	Masking test for correct operation behaviour in presence of various appliances connected to the load side	37
8.17	Performance of the AFD test device	37
9	Testing procedure	38
9.1	General	38
9.1.1	General testing procedure for the different type of AFDDs	38
9.1.2	The characteristics of AFDDs are checked by means of type tests	38
9.1.3	For certification purposes, type tests are carried out in test sequences	39
9.1.4	Routine tests to be carried out by the manufacturer on each device	39
9.2	Test conditions	39
9.3	Test of indelibility of marking	40
9.4	Test of reliability of screws, current-carrying parts and connections	41
9.5	Test of reliability of terminals for external conductors	42
9.6	Verification of protection against electric shock	43
9.7	Test of dielectric properties	44
9.7.1	General	44
9.7.2	Resistance to humidity	44
9.7.3	Insulation resistance of the main circuit	44
9.7.4	Dielectric strength of the main circuit.....	45
9.7.5	Insulation resistance and dielectric strength of auxiliary circuits	46
9.7.6	Capability of control circuits connected to the main circuit in respect of withstanding high d.c. voltages due to insulation measurements.....	46
9.7.7	Verification of impulse withstand voltages (across clearances and across solid insulation) and of leakage current across open contacts	47
9.8	Test of temperature-rise	50

9.8.1	Ambient air temperature	50
9.8.2	Test procedure	51
9.8.3	Measurement of the temperature of parts	51
9.8.4	Temperature-rise of a part	51
9.9	Verification of the operating characteristics	51
9.9.1	General	51
9.9.2	Series arc fault tests	51
9.9.3	Parallel arc fault tests	54
9.9.4	Masking test, verification of correct operation	56
9.9.5	Unwanted tripping test	57
9.10	Verification of mechanical and electrical endurance	58
9.10.1	General test conditions	58
9.10.2	Test procedure	59
9.10.3	Condition of the AFDD after test	59
9.11	Verification of the behaviour of the AFDD under short-circuit conditions	59
9.11.1	General	59
9.11.2	Short-circuit tests for AFDDs according to 4.1.1	60
9.12	Verification of resistance to mechanical shock and impact	68
9.12.1	Mechanical shock	68
9.12.2	Mechanical impact	68
9.13	Test of resistance to heat	71
9.14	Test of resistance to abnormal heat and to fire	72
9.15	Verification of the trip-free mechanism	73
9.15.1	General test conditions	73
9.15.2	Test procedure	73
9.16	Test of resistance to rusting	73
9.17	Verification of limiting values of the non-operating current under overcurrent conditions	73
9.18	Verification of behaviour of AFDDs in case of current surges caused by impulse voltages	74
9.18.1	General	74
9.18.2	Verification of behaviour at surge currents up to 3 000 A (8/20 μ s surge current test)	74
9.19	Verification of reliability	74
9.19.1	General	74
9.19.2	Climatic test	75
9.19.3	Test with temperature of 40 °C	76
9.20	Verification of ageing of electronic components	77
9.21	Electromagnetic compatibility (EMC)	77
9.21.1	General	77
9.21.2	EMC tests covered by other clauses of the present standard	77
9.21.3	EMC tests to be performed	77
9.21.4	AFDDs Performance criteria	79
9.22	Verification of protection due to overvoltage due to a broken neutral in a three phase system	80
Annex A (normative)	Test sequence and number of samples to be submitted for certification purposes	102
Annex B (normative)	Determination of clearances and creepage distances	109
Annex C (normative)	Arrangement for the detection of the emission of ionized gases during short-circuit tests	114

Annex D (normative) Additional requirements and tests for AFDDs according to the classification 4.1.3 designed to be assembled on site together with a main protective device (circuit-breaker or RCCB or RCBO)	117
Annex E (normative) Routine tests	121
Annex F (informative) Description of the shaker arc test in 9.10.2	122
Annex IA (informative) Methods of determination of short-circuit power-factor	124
Annex IB (informative) Examples of terminal designs	126
Annex IC (informative) Correspondence between ISO and AWG copper conductors	129
Annex ID (informative) Follow-up testing program for AFDDs	130
Annex IE (informative) SCPDs for short-circuit tests	134
Annex J (normative) Particular requirements for AFDDs with screwless type terminals for external copper conductors	136
Annex K (normative) Particular requirements for AFDDs with flat quick-connect terminations	144
Annex L (normative) Specific requirements for AFDDs with screw-type terminals for external untreated aluminium conductors and with aluminium screw-type terminals for use with copper or with aluminium conductors	151
Bibliography	161
Figure 1 – Thread forming tapping screw	80
Figure 2 – Thread cutting tapping screw	80
Figure 3 – Standard test finger (9.6)	81
Figure 4 – Test circuit for series arc fault tests	82
Figure 5 – Arc generator	82
Figure 6 – Test circuit for parallel arc fault tests	82
Figure 7 – Test circuit for parallel arc cable cutting test	82
Figure 8 – Test apparatus	83
Figure 9 – Test for verification of correct operation in case of parallel arc to ground	83
Figure 10 – Test circuit for masking tests (inhibition and disturbing loads)	83
Figure 11 – Test configuration for masking tests	84
Figure 12 – EMI filter 1 for masking tests	84
Figure 13 – EMI filter 2 for masking tests	85
Figure 14 – EMI filter description installed in Figure 13	85
Figure 15 – Test circuit for masking tests with line impedance	85
Figure 16 – Cross talk test	86
Figure 17 – Controlled current test circuit	86
Figure 18 – Controlled current with delay angle 45 °, 90 ° and 135 °	87
Figure 19 – Short circuit test	88
Figure 20 – Typical diagram for short circuit tests ((9.11.2.4c)	89
Figure 21 – Detail of impedance Z, Z ₁ and Z ₂	90
Figure 22 – Example of calibration record for short-circuit test (9.11.2.2 j)	90
Figure 23 – Mechanical shock test apparatus (9.12.1)	91
Figure 24 – Mechanical impact test apparatus (9.12.2.2)	92
Figure 25 – Striking element for pendulum impact test apparatus (9.12.2.2)	93
Figure 26 – Mounting support for sample for mechanical impact test (9.12.2.2)	94

Figure 27 – Example of mounting of unenclosed AFDD for mechanical impact test (9.12.2.2)	95
Figure 28 – Example of mounting of panel mounting type AFDD for the mechanical impact test (9.12.2.2)	96
Figure 29 – Application of force for mechanical test of rail mounted AFDD (9.12.2.3)	97
Figure 30 – Ball-pressure test apparatus (9.13.2)	97
Figure 31 – Surge current impulse 8/20 μ s	98
Figure 32 – Test circuit for the surge current test at AFDDs	98
Figure 33 – Stabilizing period for reliability test (9.19.2.3)	99
Figure 34 – Reliability test cycle (9.19.2.3)	100
Figure 35 – Example for test circuit for verification of ageing of electronic components (9.20)	101
Figure 36 – Preparation of the cable specimens (9.9.2.6)	101
Figure 37 – Example of arc voltage and current waveform obtained with cable specimen	101
Figure C.1 – Test arrangement	115
Figure C.2 – Grid	116
Figure C.3 – Grid circuit	116
Figure F.1 – Gap Measurement	122
Figure F.2 – Shaker arc test table with Loose Terminals	122
Figure F.3 – AFDD connected to the shaker arc table during test	123
Figure IB.1 – Examples of pillar terminals	126
Figure IB.2 – Examples of screw terminals and stud terminals	127
Figure IB.3 – Examples of saddle terminals	128
Figure IB.4 – Examples of lug terminals	128
Figure IE-1 – Test apparatus for the verification of the minimum I^2t and I_p values to be withstood by the AFDD	135
Figure J.1 – Connecting samples	141
Figure J.2 – Examples of screwless-type terminals	143
Figure K.1 – Example of position of the thermocouple for measurement of the temperature-rise	147
Figure K.2 – Dimensions of male tabs	148
Figure K.3 – Dimensions of round dimple detents (see Figure K.2)	149
Figure K.4 – Dimensions of rectangular dimple detents (see Figure K.2)	149
Figure K.5 – Dimensions of hole detents	149
Figure K.6 – Dimensions of female connectors	150
Figure L.1 – General arrangement for the test	159
Figure L.2 – Example for the use of the terminals in the AFDD	159
Figure L.3 – Example for the use of the terminals in the AFDD	160
Figure L.4 – Example for the use of the terminals in the AFDD	160
Figure L.5 – Example for the use of the terminals in the AFDD	160
Figure L.6 – Example for the use of the terminals in the AFDD	160
Table 1 – Limit values of break time for $U_n = 230$ V AFDDs	20
Table 2 – Limit values of break time for $U_n = 120$ V AFDDs	20

Table 3 – Maximum allowed number of arcing half-cycles within 0,5 s for U_n 230 V AFDDs and $U_n = 120$ V AFDDs	20
Table 4 – Rated impulse withstand voltage as a function of the nominal voltage of the installation	21
Table 5 – Marking and position of marking	22
Table 6 – Standard conditions for operation in service	25
Table 7 – Minimum clearances and creepage distances	29
Table 8 – Connectable cross-sections of copper conductors for screw-type terminals	32
Table 9 – Temperature-rise values	35
Table 10 – List of type tests	39
Table 11 – Test copper conductors corresponding to the rated currents	40
Table 12 – Screw thread diameters and applied torques	41
Table 13 – Pulling forces	42
Table 14 – Test voltage of auxiliary circuits	46
Table 15 – Test voltage for verification of impulse withstand voltage	48
Table 16 – Test voltage for verifying the suitability for isolation, referred to the rated impulse withstand voltage of the AFDD and the altitude where the test is carried out	49
Table 17 – Tests to be made to verify the behaviour of AFDDs under short-circuit conditions	61
Table 18 – Minimum values of I^2t and I_p	62
Table 19 – Power factors for short-circuit tests	63
Table 20 – Tests already covered in this standard	77
Table 21 – Tests to be applied for EMC	78
Table A.1 – Test sequences for AFDDs classified according to 4.1.1	103
Table A.2 – Test sequences for AFDDs classified according to 4.1.2	104
Table A.3 – Test sequences for AFDDs classified according to 4.1.3	105
Table A.4 – Number of samples for full test procedure	106
Table A.5 – Number of samples for simplified test procedure	108
Table ID.1 – Test sequences during follow-up inspections	130
Table ID.2 – Number of samples to be tested	133
Table IE.1 – Indication of silver wire diameters as a function of rated currents and short-circuit currents	134
Table J.1 – Connectable conductors	138
Table J.2 – Cross-sections of copper conductors connectable to screwless-type terminals	139
Table J.3 – Pull forces	140
Table K.1 – Informative table on colour code of female connectors in relationship with the cross section of the conductor	145
Table K.2 – Overload test forces	146
Table K.3 – Dimensions of tabs	147
Table K.4 – Dimensions of female connectors	150
Table L.1 – Marking for terminals	152
Table L.2 – Connectable cross-sections of aluminium conductors for screw-type terminals	153
Table L.3 – List of tests according to the material of conductors and terminals	154
Table L.4 – Connectable conductors and their theoretical diameters	154

Table L.5 – Cross sections (S) of aluminium test conductors corresponding to the rated currents	155
Table L.6 – Test conductor length	156
Table L.7 – Equalizer and busbar dimensions	156
Table L.8 – Test current as a function of rated current	158
Table L.9 – Example of calculation for determining the average temperature deviation D	158

This document is a preview generated by EVS

INTERNATIONAL ELECTROTECHNICAL COMMISSION

GENERAL REQUIREMENTS FOR ARC FAULT DETECTION DEVICES**FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62606 has been prepared by subcommittee 23E: Circuit-breakers and similar equipment for household use, of IEC technical committee 23: Electrical accessories.

The text of this standard is based on the following documents:

FDIS	Report on voting
23E/785/FDIS	23E/797/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

In this standard, the following print types are used:

- *compliance statements: in italic type.*

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

This International Standard aims to provide necessary requirements and testing procedures for devices to be installed by skilled people in households and similar uses to mitigate the risk of igniting an electrical fire downstream of the device.

Residual Current Devices (RCDs) are recognised as efficient to reduce the risk of fire by detection of leakage current and arcing to ground as a consequence of tracking currents within an electrical installation. However, RCDs as fuses or circuit-breakers are not able to reduce the risk of electrical fire due to series or parallel arcing between live conductors.

During a series arc fault, there is no leakage to ground therefore RCDs cannot detect such a fault. Moreover, the impedance of the series arc fault reduces the load current, which will keep the current below the tripping threshold of the circuit-breaker and the fuse. In the case of a parallel arc between phase and neutral conductor, the current is only limited by the impedance of the installation. In the worst cases of sporadic arcs, the conventional circuit breakers were not designed for that purpose.

Experience and information available confirmed that the r.m.s. current value of an earth fault current caused by an arcing fault, which is able to ignite a fire, is not limited to the rated power supply frequency of 50/60 Hz, but may contain a much higher frequency spectrum that is not taken into account for the testing of RCDs.

It has been recognised that the risk of igniting a fire within an electrical installation can also be a consequence of an overvoltage due to a broken neutral in a three phase installation.

This standard covers devices designed to be installed in a distribution board at the origin of one or several final circuits of a fixed installation.

GENERAL REQUIREMENTS FOR ARC FAULT DETECTION DEVICES

1 Scope

This International Standard applies to arc fault detection devices (AFDD) for household and similar uses in a.c. circuits.

NOTE 1 In the USA, Arc Fault Circuit Interrupters (AFCI) are considered similar to AFDDs.

An AFDD is designed by the manufacturer:

- either as a single device having opening means able to open the protected circuit in specified conditions; or
- as a single device integrating a protective device; or
- as a separate unit, according to Annex D assembled on site with a declared protective device.

The integrated protection device is either a circuit-breaker in accordance with IEC 60898-1 or an RCD in accordance with IEC 61008-1, IEC 61009-1 or IEC 62423.

These devices are intended to mitigate the risk of fire in final circuits of a fixed installation due to the effect of arc fault currents that pose a risk of fire ignition under certain conditions if the arcing persists.

Protection against fire ignition due to overvoltage due to a broken neutral within a three phase installation to be included in this type of equipment as an additional option is under consideration in 9.22.

NOTE 2 Tracking current leads to arcing and therefore may ignite fire.

This International Standard applies to devices performing simultaneously the detection and discrimination of arcing current with regards to fire hazards and defines operating criteria under specified conditions for the opening of the circuit when the arcing current exceeds the limit values given in this standard.

AFDDs complying with this standard, with the exception of those with an uninterrupted neutral, are suitable for use in IT systems.

The maximum rated voltage is 240 V a.c. AFDDs, according to this standard, are supplied either between line and neutral or between two lines.

The maximum rated current (I_n) is 63 A a.c.

AFDDs energised from batteries or a circuit other than the protected circuit are not covered by this standard.

AFDDs provide isolation, they are intended to be operated by uninstructed persons and do not require maintenance.

Particular requirements may be necessary for:

- AFDDs incorporated in or intended only for association with plugs and socket-outlets or with appliance couplers for household or similar general purposes;
- AFDDs intended to be used at frequencies other than 50 Hz or 60 Hz.

NOTE 3 For AFDDs incorporated in, or intended only for socket-outlets the requirements of this standard can be used, as far as applicable, in conjunction with the requirements of IEC 60884-1 or the national requirements of the country where the product is placed on the market.

NOTE 4 In the UK, the plug part and the socket-outlet part(s) need not comply with any IEC 60884-1 requirements. In the UK, the plug part shall comply with BS 1363-1 and the socket-outlet part(s) shall comply with BS 1363-2.

Special precautions (e.g. surge protective devices) may be necessary when excessive overvoltages are likely to occur on the supply side.

The requirements of this standard apply for standard conditions of temperature and environment. They are applicable to AFDDs intended for use in an environment with pollution degree 2. Additional requirements may be necessary for devices used in locations having more severe environmental conditions.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-30:2005, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 + 12 h cycle)*

IEC 60068-3-4:2001, *Environmental testing – Part 3-4: Supporting documentation and guidance – Damp heat tests*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60364-4-44:2007, *Low-voltage electrical installations – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*

IEC 60417, *Graphical symbols for use on equipment*, available from: <<http://www.graphical-symbols.info/equipment>>

IEC 60479 (all parts), *Effects of current on human beings and livestock*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60664-1:2007, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60695-2-10:2000, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC/TR 60755, *General requirements for residual current operated protective devices*

IEC 60898-1:2002, *Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations – Part 1: Circuit-breakers for a.c. operation*

IEC 61008-1:2010, *Residual current operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs) – Part 1: General rules*

IEC 61009-1:2010, *Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs) – Part 1: General rules*

IEC 61543:1995, *Residual current-operated protective devices (RCDs) for household and similar use – Electromagnetic compatibility*
 Amendment 1:2004
 Amendment 2:2005

IEC 62423, *Type F and type B residual current operated circuit-breakers with and without integral overcurrent protection for household and similar uses*

CISPR 14-1:2009, *Electromagnetic compatibility – Requirements for household appliances, electric tools and similar apparatus – Part 1: Emission*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC/TR 60755, IEC 60898-1, IEC 61008-1, IEC 61009-1, IEC 62423 and the following apply.

NOTE Where the terms "voltage" or "current" are used, they imply r.m.s. values, unless otherwise specified.

3.1

arc arcing

luminous discharge of electricity across an insulating medium, usually accompanied by the partial volatilization of the electrodes

Note 1 to entry: A complete sinusoidal current half cycle is not considered to be an arcing half cycle.

3.2

arc fault arcing fault

dangerous unintentional parallel or series arc between conductors

3.3

arc fault detection device AFDD

device intended to mitigate the effects of arcing faults by disconnecting the circuit when an arc fault is detected

3.4

arc fault detection unit AFD unit

part of the AFDD ensuring the function of detection and discrimination of dangerous earth, parallel and series arc faults and initiating the operation of the device to cause interruption of the current

Note 1 to entry: The interruption of the current can either be provided by opening means (see 4.1.1) or by a protective device integrating an AFD unit (see 4.1.2) or by a protective device assembled with an AFD unit see (4.1.3).

3.5

detection

function consisting in sensing the presence of an arc fault current

3.6

interruption

function consisting in bringing automatically the main contacts of the AFDD from the closed position into the open position, thereby interrupting the arc fault current(s) flowing through them