

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**High-voltage switchgear and controlgear –
Part 109: Alternating-current series capacitor by-pass switches**

**Appareillage à haute tension –
Partie 109: Interrupteurs de contournement pour condensateurs série à courant
alternatif**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00



IEC 62271-109

Edition 2.0 2008-11

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**High-voltage switchgear and controlgear –
Part 109: Alternating-current series capacitor by-pass switches**

**Appareillage à haute tension –
Partie 109: Interrupteurs de contournement pour condensateurs série à courant
alternatif**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

XF

ICS 29.130.10

ISBN 2-8318-1013-6

CONTENTS

FOREWORD.....	8
1 General	10
1.1 Scope.....	10
1.2 Normative references	10
2 Normal and special service conditions	11
3 Terms and definitions	11
3.1 General terms	11
3.2 Assemblies.....	13
3.3 Parts of assemblies	13
3.4 Switching devices.....	13
3.5 Parts of by-pass switches	15
3.6 Operation	17
3.7 Characteristic quantities	18
3.8 Definitions related to series capacitor banks.....	22
3.9 Index of definitions	25
4 Ratings.....	28
4.1 Rated voltage (U_r)	28
4.2 Rated insulation level	29
4.2.101 Rated insulation level to earth	29
4.2.102 Rated insulation level across the by-pass switch	29
4.3 Rated frequency (f_r).....	29
4.4 Rated normal current (I_r) and temperature rise	29
4.5 Rated short-time withstand current (I_k)	29
4.6 Rated peak withstand current (I_p)	30
4.7 Rated duration of short-circuit (t_k)	30
4.8 Rated supply voltage of closing and opening devices and of auxiliary and control circuits (U_a)	30
4.9 Rated supply frequency of closing and opening devices and auxiliary circuits.....	30
4.10 Rated pressures of compressed gas supply for insulation, operation and/or by-passing and insertion	30
4.101 Rated operating sequence	30
4.102 Rated by-pass making current (I_{BP})	30
4.104 Rated reinsertion voltage (U_{INS})	31
4.105 Rated time quantities	32
4.106 Number of mechanical operations.....	32
5 Design and construction	32
5.1 Requirements for liquids in by-pass switches.....	32
5.2 Requirements for gases in by-pass switches.....	32
5.3 Earthing of by-pass switches	32
5.4 Auxiliary equipment	32
5.5 Dependent power operation	33
5.6 Stored energy operation	34
5.7 Independent manual operation.....	34
5.8 Operation of releases	34
5.8.1 Shunt closing releases	34

5.8.2	Shunt opening releases	34
5.8.3	Capacitor operation of shunt releases	34
5.8.4	Under-voltage release	34
5.8.101	Multiple releases	34
5.8.102	Operation limits of releases	34
5.8.103	Power consumption of releases	34
5.9	Low- and high-pressure interlocking devices	35
5.10	Nameplates	35
5.11	Interlocking devices	37
5.12	Position indication	37
5.13	Degrees of protection by enclosures	37
5.14	Creepage distances	37
5.15	Gas and vacuum tightness	37
5.16	Liquid tightness	37
5.17	Fire hazard (flammability)	37
5.18	Electromagnetic compatibility	37
5.19	X-ray emission	38
5.20	Corrosion	38
5.101	Requirements for simultaneity within a pole	38
5.102	General requirement for operation	38
5.103	Pressure limits of fluids for operation	38
5.104	Vent outlets	38
6	Type tests	39
6.1	General	40
6.1.1	Grouping of tests	40
6.1.2	Information for identification of specimens	40
6.1.3	Information to be included in type test reports	40
6.2	Dielectric tests	41
6.2.1	Ambient air conditions during tests	41
6.2.2	Wet test procedure	41
6.2.3	Condition of by-pass switch during dielectric tests	41
6.2.4	Criteria to pass the test	41
6.2.5	Application of test voltage and test conditions	42
6.2.6	Tests of by-pass switches of $U_{re} \leq 245$ kV or $U_{rp} \leq 245$ kV	42
6.2.7	Tests of by-pass switches of $U_{re} > 245$ kV or $U_{rp} > 245$ kV	42
6.2.8	Artificial pollution tests	43
6.2.9	Partial discharge tests	43
6.2.10	Tests on auxiliary and control circuits	43
6.2.11	Voltage test as a condition check	43
6.3	Radio interference voltage (r.i.v.) tests	44
6.4	Measurement of the resistance of the main circuit	44
6.5	Temperature-rise tests	45
6.5.1	Conditions of the by-pass switch to be tested	45
6.5.2	Arrangement of the equipment	45
6.5.3	Measurement of the temperature and the temperature rise	45
6.5.4	Ambient air temperature	45
6.5.5	Temperature-rise tests of the auxiliary and control equipment	45
6.5.6	Interpretation of the temperature-rise tests	45

6.6	Short-time withstand current and peak withstand current tests	45
6.6.1	Arrangement of the by-pass switch and of the test circuit	45
6.6.2	Test current and duration.....	45
6.6.3	Behaviour of the by-pass switch during test.....	45
6.6.4	Conditions of the by-pass switch after test.....	45
6.7	Verification of the degree of protection	45
6.7.1	Verification of the IP coding.....	45
6.7.2	Mechanical impact test (verification of the IK coding)	45
6.8	Tightness tests	46
6.9	Electromagnetic compatibility (EMC) tests	46
6.10	Additional tests on auxiliary and control circuits	46
6.10.1	General	46
6.10.2	Functional tests	46
6.10.3	Electrical continuity of earthed metallic parts test	46
6.10.4	Verification of the operational characteristics of auxiliary contacts	46
6.10.5	Environmental tests	46
6.11	X-Radiation test procedure for vacuum interrupters	47
6.101	Mechanical and environmental tests	47
6.101.1	Miscellaneous provisions for mechanical and environmental tests	47
6.101.2	Mechanical operation test at ambient air temperature.....	49
6.101.3	Low and high temperature tests	51
6.101.4	Humidity test	55
6.101.5	Test to prove the operation under severe ice conditions	55
6.101.6	Static terminal load test.....	55
6.102	Miscellaneous provisions for by-pass making and insertion tests	57
6.102.1	General	57
6.102.2	Number of test specimens.....	57
6.102.3	Arrangement of by-pass switch for tests	57
6.102.4	General considerations concerning testing methods	59
6.102.5	Synthetic tests	61
6.102.6	No-load operations before tests.....	61
6.102.7	Alternative operating mechanisms	61
6.102.8	Behaviour of by-pass switch during tests.....	62
6.102.9	Condition of by-pass switch after tests	62
6.103	Sequence of the tests	64
6.104	By-pass making current test-duty.....	64
6.104.1	General	64
6.104.2	Characteristics of supply circuit.....	64
6.104.3	Test voltage	65
6.104.4	Test current.....	65
6.105	Insertion current test-duty.....	66
6.105.1	General	66
6.105.3	Test voltage	67
6.105.4	Test current.....	67
6.105.5	Number of operations	67
6.106	Criteria to pass the test duties	68
7	Routine tests	68
7.1	Dielectric test on the main circuit	68

7.2	Dielectric test on auxiliary and control circuits	69
7.3	Measurement of the resistance of the main circuit	69
7.4	Tightness test	69
7.5	Design and visual checks	69
7.101	Mechanical operating tests	69
8	Guide to the selection of by-pass switches for service	70
9	Information to be given with enquiries, tenders and orders	71
9.101	Information to be given with enquiries and orders	71
9.102	Information to be given with tenders	72
10	Rules for transport, storage, installation, operation and maintenance	73
10.1	Conditions during transport, storage and installation	73
10.2	Installation	73
10.2.101	Guide for commissioning tests	73
10.2.102	Commissioning checks and test programme	74
10.3	Operation	79
10.4	Maintenance	79
10.4.101	Resistors and capacitors (if applicable)	80
11	Safety	80
12	Influence of the product on environment	80
Annex A (normative)	Tolerances on test quantities during type tests	98
Annex B (normative)	Records and reports of type tests	102
Annex C (informative)	List of symbols and abbreviations used	105
Annex D (informative)	Examples of by-pass switch ratings	107
Annex E (informative)	By-pass switches used as the primary by-passing devices	114
Annex F (informative)	Explanatory note regarding transient recovery voltage during reinsertion	115
Annex G (normative)	Use of mechanical characteristics and related requirements	125
Bibliography	127
Figure 1	By-pass switch – Opening and closing operations	81
Figure 2	By-pass switch – Close-open cycle	82
Figure 3	By-pass switch – Open-close cycle	83
Figure 4	Test sequences for low and high temperature tests	84
Figure 5	Static terminal load forces	85
Figure 6	Directions for static terminal load tests	86
Figure 7	Reference mechanical travel characteristics (idealized curve)	87
Figure 8	Reference mechanical travel characteristics (idealized curve) with the prescribed envelopes centred over the reference curve ($\pm 5\%$), contact separation in this example at time $t = 20$ ms	87
Figure 9	Reference mechanical travel characteristics (idealized curve) with the prescribed envelopes fully displaced upward from the reference curve ($^{+10}_0\%$), contact separation in this example at time $t = 20$ ms	88
Figure 10	Reference mechanical travel characteristics (idealized curve) with the prescribed envelopes fully displaced downward from the reference curve ($^0_{-10}\%$), contact separation in this example at time $t = 20$ ms	88

Figure 11 – Equivalent testing set-up for unit testing of by-pass switches with more than one separate by-pass units	89
Figure 12 – Typical test circuit for the by-pass making current test-duty	90
Figure 13 – Oscillogram obtained from the typical test circuit for the by-pass making current test-duty	91
Figure 14 – Typical LC test circuit for the insertion current test-duty	92
Figure 15 – Oscillogram obtained from the typical LC test circuit for the insertion current test-duty	93
Figure 16 – Typical test circuit for the insertion current test-duty (mainly for high rated insertion current)	94
Figure 17 – Oscillogram obtained from the typical test circuit shown in Figure 16 for the insertion current test-duty	95
Figure 18 – Typical direct test circuit for the insertion current test-duty	96
Figure 19 – Oscillogram obtained from the typical direct test circuit for the insertion current test-duty	97
Figure E.1 – Typical components layout for by-pass switches used as the primary by-passing device	114
Figure F.1 – Typical example of the transient reinsertion voltage across a by-switch for a low compensation factor scheme ($k = 0,2$) and for a power swing of 1,8 p.u.	121
Figure F.2 – Typical example of the transient reinsertion voltage across a by-switch for an high compensation factor scheme ($k = 0,5$) and for a power swing of 1,8 p.u.	122
Figure F.3 – Comparison of the calculated transient reinsertion voltage examples and possible testing envelopes for 50 Hz systems	122
Figure F.4 – Comparison of the calculated transient reinsertion voltage examples and possible testing envelopes for 60 Hz systems	123
Table 1 – Nameplate information	36
Table 2 – Type tests	40
Table 3 – Invalid tests	41
Table 4 – Number of operating sequences	50
Table 5 – Examples of static horizontal and vertical forces for static terminal load test	56
Table 6 – Application of voltage for dielectric test on the main circuit	68
Table A.1 – Tolerances on test quantities for type tests	99
Table D.1 – Typical ratings for a series capacitor bank by-pass switch – Cases 1 to 6	108
Table D.2 – Typical series capacitor bank by-pass switch ratings – Cases 7 to 12	110
Table D.3 – Typical series capacitor bank by-pass switch ratings – Cases 13 to 18	112
Table F.1 – Typical examples of transient reinsertion voltages for systems not having power swing nor emergency overload, $I_{load} = 1,0$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz	116
Table F.2 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,2$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz	116
Table F.3 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,4$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz	116
Table F.4 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,6$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz	117

Table F.5 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 1,8$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz.....	117
Table F.6 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 2,0$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz.....	117
Table F.7 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 2,3$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz.....	118
Table F.8 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 2,5$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 50$ Hz.....	118
Table F.9 – Typical examples of transient reinsertion voltages for systems not having power swing nor emergency overload, $I_{load} = 1,0$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	118
Table F.10 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,2$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	119
Table F.11 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,4$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	119
Table F.12 – Typical examples of transient reinsertion voltages for systems not having power swing but with an emergency overload, $I_{load} = 1,6$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	119
Table F.13 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 1,8$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	120
Table F.14 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 2,0$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	120
Table F.15 – Typical examples of transient reinsertion voltages for systems having power swing, $I_{load} = 2,3$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	120
Table F.16 – Typical examples of reinsertion recovery voltages for systems having power swing, $I_{load} = 2,5$ p.u.; $U_{PL} = 2,2$ p.u.; $\beta = 0,85$ and $f = 60$ Hz.....	121
Table G.1 – Summary of type tests related to mechanical characteristics	126

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

**Part 109: Alternating-current series capacitor
by-pass switches**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62271-109 has been prepared by subcommittee 17A: High-voltage switchgear and controlgear, of IEC technical committee 17: Switchgear and controlgear.

This second edition cancels and replaces the first edition, published in 2006, and constitutes a technical revision.

The main changes with respect to the previous edition are listed below:

- By-passing test duty has been split with operations at rated by-pass making current I_{BP} and operations at capacitor bank discharge current $I_{DISCHARGE}$.
- Equivalence regarding applicability of test parameters (current peak and frequency) during by-pass making tests in relation with service conditions have been reviewed and changed accordingly.
- Recovery voltage waveshape during insertion test duty has been recalculated and optimized. An explanatory note on the calculation of the recovery voltage is given in Annex F.

- Withdrawal of the electrical endurance class BP2. Such devices are now covered in informative Annex E
- Addition of Annex D which gives examples of typical by-pass switch ratings.

The text of this standard is based on the following documents:

FDIS	Report on voting
17A/837/FDIS	17A/844/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the IEC 62271 series can be found, under the general title *High-voltage switchgear and controlgear*, on the IEC website.

This standard is to be read in conjunction with IEC 62271-100 and IEC 62271-1 (2007), to which it refers and which is applicable, unless otherwise specified in this standard. In order to simplify the indication of corresponding requirements, the same numbering of clauses and subclauses is used as in IEC 62271-1. Amendments to these clauses and subclauses are given under the same references whilst additional subclauses are numbered from 101.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 109: Alternating-current series capacitor by-pass switches

1 General

1.1 Scope

This part of IEC 62271 is applicable to a.c. series capacitor by-pass switches designed for outdoor installation and for operation at frequencies of 50 Hz and 60 Hz on systems having voltages above 52 kV.

It is only applicable to by-pass switches for use in three-phase systems.

This standard is also applicable to the operating devices of by-pass switches and to their auxiliary equipment.

1.2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-151:2001, *International Electrotechnical Vocabulary – Part 151: Electrical and magnetic devices*

IEC 60050-436:1990, *International Electrotechnical Vocabulary – Chapter 436: Power capacitors*

IEC 60050-441:1984, *International Electrotechnical Vocabulary – Chapter 441: Switchgear, controlgear and fuses*

IEC 60050-604:1987, *International Electrotechnical Vocabulary – Chapter 604: Generation, transmission and distribution of electricity – Operation*

IEC 60060 (all parts), *High-voltage test techniques*

IEC 60143-1:2004, *Series capacitors for power systems – Part 1: General*

IEC 60143-2:1994, *Series capacitors for power systems – Part 2: Protective equipment for series capacitor banks*

IEC 60296, *Fluids for electrotechnical applications – Unused mineral insulating oils for transformers and switchgear*

IEC 60376, *Specification of technical grade sulphur hexafluoride (SF₆) for use in electrical equipment*

IEC 60480, *Guidelines for the checking and treatment of sulphur hexafluoride (SF₆) taken from electrical equipment and specification for its re-use*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 62271-1:2007, *High-voltage switchgear and controlgear – Part 1: Common specifications*

IEC 62271-100:2008, *High-voltage switchgear and controlgear – Part 100: Alternating-current circuit-breakers*

IEC 62271-101, *High-voltage switchgear and controlgear – Part 101: Synthetic testing*

IEC 62271-102:2001, *High-voltage switchgear and controlgear – Part 102: Alternating current disconnectors and earthing switches*

IEC 62271-303, *High-voltage switchgear and controlgear – Part 303: Use and handling of sulphur hexafluoride (SF₆)*

2 Normal and special service conditions

Clause 2 of IEC 62271-1 is applicable.

3 Terms and definitions

For the purposes of this document, the terms and definitions of IEC 60050-151, IEC 60050-436, IEC 60050-441, IEC 60050-604, IEC 60143-1, IEC 60143-2 and IEC 62271-1 apply. Some of them are recalled here for ease of reference.

Additional terms and definitions are classified so as to be aligned with the classification used in IEC 60050-441.

3.1 General terms

3.1.101

switchgear and controlgear

[IEV 441-11-01]

3.1.102

outdoor switchgear and controlgear

[IEV 441-11-05]

3.1.103

short-circuit current

[IEV 441-11-07]

3.1.104

ambient air temperature

[IEV 441-11-13]

3.1.105

temperature rise (of a part of a by-pass switch)

difference between the temperature of the part and the ambient air temperature

3.1.106

overvoltage (in a system)

any voltage between one phase and earth or between phases having a peak value or values exceeding the corresponding peak of the highest voltage for equipment

[IEV 604-03-09, modified]