

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Residual current operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs) –
Part 1: General rules**

**Interrupteurs automatiques à courant différentiel résiduel sans dispositif de protection contre les surintensités incorporé pour usages domestiques et analogues (ID) –
Partie 1: Règles générales**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2010 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Residual current operated circuit-breakers without integral overcurrent
protection for household and similar uses (RCCBs) –
Part 1: General rules**

**Interrupteurs automatiques à courant différentiel résiduel sans dispositif de
protection contre les surintensités incorporé pour usages domestiques et
analogues (ID) –
Partie 1: Règles générales**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

XF

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	10
1 Scope.....	11
2 Normative references	12
3 Terms and definitions	13
3.1 Definitions relating to currents flowing from live parts to earth	13
3.2 Definitions relating to the energization of a residual current circuit-breaker	13
3.3 Definitions relating to the operation and functions of residual current circuit-breakers	14
3.4 Definitions relating to values and ranges of energizing quantities	16
3.5 Definitions relating to values and ranges of influencing quantities	18
3.6 Definitions relating to terminals	19
3.7 Definitions relating to conditions of operation	20
3.8 Definitions relating to tests	21
3.9 Definitions relating to insulation coordination.....	21
4 Classification.....	23
4.1 According to the method of operation	23
4.1.1 RCCB functionally independent of line voltage (see 3.3.4).....	23
4.1.2 RCCB functionally dependent on line voltage (see 3.3.5).....	23
4.2 According to the type of installation	23
4.3 According to the number of poles and current paths	23
4.4 According to the possibility of adjusting the residual operating current	23
4.5 According to resistance to unwanted tripping due to voltage surges	23
4.6 According to behaviour in presence of d.c. components	23
4.7 According to time-delay (in presence of a residual current)	24
4.8 According to the protection against external influences	24
4.9 According to the method of mounting	24
4.10 According to the method of connection	24
5 Characteristics of RCCBs	24
5.1 Summary of characteristics	24
5.2 Rated quantities and other characteristics	25
5.2.1 Rated voltage (U_n)	25
5.2.2 Rated current (I_n)	25
5.2.3 Rated residual operating current ($I_{\Delta n}$).....	25
5.2.4 Rated residual non-operating current ($I_{\Delta no}$).....	25
5.2.5 Rated frequency	25
5.2.6 Rated making and breaking capacity (I_m)	25
5.2.7 Rated residual making and breaking capacity ($I_{\Delta m}$)	26
5.2.8 RCCB type S	26
5.2.9 Operating characteristics in case of residual currents with d.c. components	26
5.3 Standard and preferred values	26
5.3.1 Preferred values of rated voltage (U_n)	26
5.3.2 Preferred values of rated current (I_n).....	27
5.3.3 Standard values of rated residual operating current ($I_{\Delta n}$).....	27
5.3.4 Standard value of residual non-operating current ($I_{\Delta no}$).....	27

5.3.5	Standard minimum value of non-operating overcurrent in case of a multiphase balanced load through a multipole RCCB (see 3.4.2.1)	27
5.3.6	Standard minimum value of the non-operating overcurrent in case of a single-phase load through a three-pole or four-pole RCCB (see 3.4.2.2)	27
5.3.7	Preferred values of rated frequency	27
5.3.8	Minimum value of the rated making and breaking capacity (I_m)	27
5.3.9	Minimum value of the rated residual making and breaking capacity ($I_{\Delta m}$)	28
5.3.10	Standard and preferred values of the rated conditional short-circuit current (I_{nc})	28
5.3.11	Standard values of the rated conditional residual short-circuit current ($I_{\Delta c}$)	28
5.3.12	Limit values of break time and non-actuating time for RCCB of type AC and A	28
5.3.13	Standard value of rated impulse withstand voltage (U_{imp})	29
5.4	Coordination with short-circuit protective devices (SCPDs)	30
5.4.1	General	30
5.4.2	Rated conditional short-circuit current (I_{nc})	30
5.4.3	Rated conditional residual short-circuit current ($I_{\Delta c}$)	30
6	Marking and other product information	30
7	Standard conditions for operation in service and for installation	32
7.1	Standard conditions	32
7.2	Conditions of installation	33
7.3	Pollution degree	33
8	Requirements for construction and operation	33
8.1	Mechanical design	33
8.1.1	General	33
8.1.2	Mechanism	33
8.1.3	Clearances and creepage distances (see Annex B)	35
8.1.4	Screws, current-carrying parts and connections	37
8.1.5	Terminals for external conductors	38
8.2	Protection against electric shock	40
8.3	Dielectric properties and isolating capability	40
8.4	Temperature-rise	41
8.4.1	Temperature-rise limits	41
8.4.2	Ambient air temperature	41
8.5	Operating characteristic	41
8.6	Mechanical and electrical endurance	41
8.7	Performance at short-circuit currents	41
8.8	Resistance to mechanical shock and impact	42
8.9	Resistance to heat	42
8.10	Resistance to abnormal heat and to fire	42
8.11	Test device	42
8.12	Requirements for RCCBs functionally dependent on line voltage	42
8.13	Behaviour of RCCBs in case of overcurrents in the main circuit	43
8.14	Behaviour of RCCBs in the case of current surges caused by impulse voltages	43
8.15	Behaviour of RCCBs in case of earth fault currents comprising a d.c. component	43

8.16	Reliability	43
8.17	Electromagnetic compatibility (EMC)	43
9	Tests	43
9.1	General	43
9.2	Test conditions	44
9.3	Test of indelibility of marking	45
9.4	Test of reliability of screws, current-carrying parts and connections	46
9.5	Test of reliability of terminals for external conductors	47
9.6	Verification of protection against electric shock	48
9.7	Test of dielectric properties	49
9.7.1	Resistance to humidity	49
9.7.2	Insulation resistance of the main circuit	49
9.7.3	Dielectric strength of the main circuit	50
9.7.4	Insulation resistance and dielectric strength of auxiliary circuits	51
9.7.5	Secondary circuit of detection transformers	51
9.7.6	Capability of control circuits connected to the main circuit withstanding high d.c. voltages due to insulation measurements	51
9.7.7	Verification of impulse withstand voltages (across clearances and across solid insulation) and of leakage current across open contacts	52
9.8	Test of temperature-rise	54
9.8.1	Ambient air temperature	54
9.8.2	Test procedure	54
9.8.3	Measurement of the temperature of parts	54
9.8.4	Temperature rise of a part	55
9.9	Verification of the operating characteristic	55
9.9.1	Test circuit	55
9.9.2	Off-load tests with residual sinusoidal alternating currents at the reference temperature of $20\text{ }^{\circ}\text{C} \pm 5\text{ }^{\circ}\text{C}$	55
9.9.3	Verification of the correct operation with load at the reference temperature	56
9.9.4	Tests at the temperature limits	56
9.9.5	Particular test conditions for RCCBs functionally dependent on line voltage	57
9.10	Verification of mechanical and electrical endurance	57
9.10.1	General test conditions	57
9.10.2	Test procedure	57
9.10.3	Condition of the RCCB after test	58
9.11	Verification of the behaviour of the RCCB under short-circuit conditions	58
9.11.1	List of the short-circuit tests	58
9.11.2	Short-circuit tests	58
9.12	Verification of resistance to mechanical shock and impact	67
9.12.1	Mechanical shock	67
9.12.2	Mechanical impact	67
9.13	Test of resistance to heat	70
9.14	Test of resistance to abnormal heat and to fire	71
9.15	Verification of the trip-free mechanism	71
9.15.1	General test conditions	71
9.15.2	Test procedure	71
9.16	Verification of the operation of the test device at the limits of rated voltage	72

9.17	Verification of the behaviour of RCCBs functionally dependent on line voltage, classified under 4.1.2.1, in case of failure of the line voltage.....	72
9.17.1	Determination of the limiting value of the line voltage (U_X).....	72
9.17.2	Verification of the automatic opening in case of failure of the line voltage	73
9.17.3	Verification of the correct operation, in presence of a residual current, for RCCBs opening with delay in case of failure of the line voltage	73
9.17.4	Verification of the correct operation of RCCBs with three or four current paths, with a residual current, one line terminal only being energized	73
9.17.5	Verification of the reclosing function of automatically reclosing RCCBs	73
9.18	Verification of limiting values of the non-operating current under overcurrent conditions.....	73
9.18.1	Verification of the limiting value of overcurrent in case of a load through an RCCB with two current paths	73
9.18.2	Verification of the limiting value of overcurrent in case of a single phase load through a three-pole or four-pole RCCB.....	74
9.19	Verification of behaviour of RCCBs in case of current surges caused by impulse voltages	74
9.19.1	Current surge test for all RCCBs (0,5 μ s/100 kHz ring wave test)	74
9.19.2	Verification of behaviour at surge currents up to 3 000 A (8/20 μ s surge current test)	75
9.20	Verification of resistance of the insulation against an impulse voltage	75
9.21	Verification of correct operation of residual currents with d.c. components	76
9.21.1	Type A residual current devices	76
9.22	Verification of reliability	77
9.22.1	Climatic test	77
9.22.2	Test with temperature of 40 °C	79
9.23	Verification of ageing of electronic components.....	80
9.24	Electromagnetic compatibility (EMC)	80
Annex A	(normative) Test sequence and number of samples to be submitted for certification purposes.....	107
Annex B	(normative) Determination of clearances and creepage distances	113
Annex C	(normative) Arrangement for the detection of the emission of ionized gases during short-circuit tests	115
Annex D	(normative) Routine tests.....	118
Annex E	(informative) Void	119
Annex IA	(informative) Methods for determination of short-circuit power-factor	120
Annex IB	(informative) Glossary of symbols	121
Annex IC	(informative) Examples of terminal designs.....	122
Annex ID	(informative) Correspondence between ISO and AWG copper conductors	125
Annex IE	(informative) Follow-up testing program for RCCBs	126
Annex IF	(informative) SCPDs for short-circuit tests	130
Bibliography		132
Figure 1	– Thread forming tapping screw (3.6.10)	80
Figure 2	– Thread cutting tapping screw (3.6.11)	81
Figure 3	– Standard test finger (9.6)	82

Figure 4 – Test circuit for the verification of	
– operating characteristics (9.9)	
– trip-free mechanism (9.15)	
– behaviour in case of failure of line voltage (9.17.3 and 9.17.4) for RCCBs	
functionally dependent on line voltage	83
Figure 5 – Test circuit for the verification of the correct operation of RCCBs in the case	
of residual pulsating direct currents	84
Figure 6 – Test circuit for the verification of the correct operation in case of residual	
pulsating direct currents in presence of a standing smooth direct current of 0,006 A	85
Figure 7 – Test circuit for the verification of the suitability of an RCCB for use in IT	
systems	87
Figure 8 – Test circuit for the verification of the rated making and breaking capacity	
and of the coordination with a SCPD of a single-pole RCCB with two current paths	
(9.11)	88
Figure 9 – Test circuit for the verification of the rated making and breaking capacity	
and of the coordination with a SCPD of a two-pole RCCB, in case of a single-phase	
circuit (9.11)	89
Figure 10 – Test circuit for the verification of the rated making and breaking capacity	
and of the coordination with a SCPD of a three-pole RCCB on three-phase circuit	
(9.11)	90
Figure 11 – Test circuit for the verification of the rated making and braking capacity	
and of the coordination with a SCPD of a three-pole RCCB with four current paths on a	
three-phase circuit with neutral (9.11)	91
Figure 12 – Test circuit for the verification of the rated making and breaking capacity	
and of the coordination with a SCPD of a four-pole RCCB on a three-phase circuit with	
neutral (9.11)	92
Figure 13 – Test apparatus for the verification of the minimum I^2t and I_p values to be	
withstood by the RCCB (9.11.2.1 a))	93
Figure 14 – Mechanical shock test apparatus (9.12.1)	94
Figure 15 – Mechanical impact test apparatus (9.12.2.1)	95
Figure 16 – Striking element for pendulum impact test apparatus (9.12.2.1)	96
Figure 17 – Mounting support for sample for mechanical impact test (9.12.2.1)	97
Figure 18 – Example of mounting and unenclosed RCCB for mechanical impact test	
(9.12.2.1)	98
Figure 19 – Example of mounting of panel mounting type RCCB for the mechanical	
impact test (9.21.2.1)	99
Figure 20 – Application of force for mechanical test of rail mounted RCCB (9.12.2.2)	100
Figure 21 – Ball-pressure test apparatus (9.13.2)	100
Figure 22 – Test circuit for the verification of the limiting value of overcurrent in case of	
single-phase load through a three-pole RCCB (9.18.2)	101
Figure 23 – Current ring wave 0,5 μ s/100 kHz	102
Figure 24 – Test circuit for the ring wave test at RCCBs	102
Figure 25 – Stabilizing period for reliability test (9.22.1.3)	103
Figure 26 – Reliability test cycle (9.22.1.3)	104
Figure 27 – Example for test circuit for verification of ageing of electronic components	
(9.23)	105
Figure 28 – Surge current impulse 8/20 μ s	105
Figure 29 – Test circuit for the surge current test at RCCBs	106
Figure 30 – Example of calibration record for short-circuit test (9.11.2.1 j) ii))	106
Figures B.1 to B.10 – Illustrations of the application of creepage distances	114

Figure C.1 – Test arrangement	116
Figure C.2 – Grid	117
Figure C.3 – Grid circuit.....	117
Figure IC.1 – Examples of pillar terminals.....	122
Figure IC.2 – Examples of screw terminals and stud terminals.....	123
Figure IC.3 – Examples of saddle terminals	124
Figure IC.4 – Examples of lug terminals.....	124
Table 1 – Limit values of break time and non-actuating time for alternating residual currents (r.m.s. values) for type AC and A RCCB	29
Table 2 – Maximum values of break time for half-wave pulsating residual currents (r.m.s. values) for type A RCCB	29
Table 3 – Rated impulse withstand voltage as a function of the nominal voltage of the installation	30
Table 4 – Standard conditions for operation in service	32
Table 5 – Minimum clearances and creepage distances.....	36
Table 6 – Connectable cross-sections of copper conductors for screw-type terminals	38
Table 7 – Temperature-rise values.....	41
Table 8 – Requirements for RCCBs functionally dependent on line voltage.....	43
Table 9 – List of type tests.....	44
Table 10 – Test copper conductors corresponding to the rated currents.....	45
Table 11 – Screw thread diameters and applied torques	46
Table 12 – Pulling forces	47
Table 13 – Conductor dimensions	48
Table 14 – Test voltage of auxiliary circuits	51
Table 15 – Test voltage across the open contacts for verifying the suitability for isolation, referred to the rated impulse withstand voltage of the RCCB and the altitude where the test is carried out.....	53
Table 16 – Test voltage for verification of impulse withstand voltage for the parts not tested in 9.7.7.1	54
Table 17 – Tests to be made to verify the behaviour of RCCBs under short-circuit conditions	58
Table 18 – Minimum values of I^2t and I_p	60
Table 19 – Power factors for short-circuit tests	61
Table 20 – Tripping current ranges for type A RCCBs	77
Table 21 – Tests to be applied for EMC	80
Table A.1 – Test sequences.....	108
Table A.2 – Number of samples for full test procedure	109
Table A.3 – Number of samples for simplified test procedure	111
Table A.4 – Test sequences for RCCBs of different classification according to 4.6	112
Table IE.1 – Test sequences during follow-up inspections	126
Table IE.2 – Number of samples to be tested.....	128
Table IF.1 – Indication of silver wire diameters as a function of rated currents and short-circuit currents	130

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**RESIDUAL CURRENT OPERATED CIRCUIT-BREAKERS
WITHOUT INTEGRAL OVERCURRENT PROTECTION
FOR HOUSEHOLD AND SIMILAR USES (RCCBs) –****Part 1: General rules****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61008-1 has been prepared by subcommittee 23E: Circuit-breakers and similar equipment for household use, of IEC technical committee 23: Electrical accessories.

This third edition cancels and replaces the second edition published in 1996, amendment 1 (2002) and amendment 2 (2006). This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- complete revision of EMC sequences, including the new test T.2.6 already approved in IEC 61543;
- clarification of RCDs current/time characteristics reported in Tables 1 and 2;
- revision of test procedure for $I_{\Delta n}$ between 5 A and 200 A;

- testing procedure regarding the 6mA d.c. current superimposed to the fault current;
- improvement highlighting RCDs with multiple sensitivity;
- tests for the use of RCCBs in IT systems.

The text of this standard is based on the following documents:

FDIS	Report on voting
23E/681/FDIS	23E/685/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the IEC 61008 series, published under the general title, *Residual current operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs)*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

This part includes definitions, requirements and tests, covering all types of RCCBs. For the applicability to a specific type this part applies in conjunction with the relevant part, as follows:

Part 2-1: Applicability of the general rules to RCCBs functionally independent of line voltage.

Part 2-2: Applicability of the general rules to RCCBs functionally dependent on line voltage.

RESIDUAL CURRENT OPERATED CIRCUIT-BREAKERS WITHOUT INTEGRAL OVERCURRENT PROTECTION FOR HOUSEHOLD AND SIMILAR USES (RCCBs) –

Part 1: General rules

1 Scope

This International Standard applies to residual current operated circuit-breakers functionally independent of, or functionally dependent on, line voltage, for household and similar uses, not incorporating overcurrent protection (hereafter referred to as RCCBs), for rated voltages not exceeding 440 V a.c. with rated frequencies of 50 Hz, 60 Hz or 50/60 Hz and rated currents not exceeding 125 A, intended principally for protection against shock hazard.

These devices are intended to protect persons against indirect contact, the exposed conductive parts of the installation being connected to an appropriate earth electrode. They may be used to provide protection against fire hazards due to a persistent earth fault current, without the operation of the overcurrent protective device.

RCCBs having a rated residual operating current not exceeding 30 mA are also used as a means for additional protection in case of failure of the protective means against electric shock.

This standard applies to devices performing simultaneously the functions of detection of the residual current, of comparison of the value of this current with the residual operating value and of opening of the protected circuit when the residual current exceeds this value.

NOTE 1 The requirements for RCCBs are in line with the general requirements of IEC 60755. RCCBs are essentially intended to be operated by uninstructed persons and designed not to require maintenance. They may be submitted for certification purposes.

NOTE 2 Installation and application rules of RCCBs are given in the IEC 60364 series.

They are intended for use in an environment with pollution degree 2.

They are suitable for isolation.

RCCBs complying with this standard, with the exception of those with an uninterrupted neutral, are suitable for use in IT systems.

Special precautions (e.g. lightning arresters) may be necessary when excessive overvoltages are likely to occur on the supply side (for example in the case of supply through overhead lines) (see IEC 60364-4-44).

RCCBs of the general type are resistant to unwanted tripping including the case where surge voltages (as a result of switching transients or induced by lightning) cause loading currents in the installation without occurrence of flashover.

RCCBs of type S are considered to be sufficient proof against unwanted tripping even if the surge voltage causes a flashover and a follow-on current occurs.

NOTE 3 Surge arresters installed downstream of the general type of RCCBs and connected in common mode may cause unwanted tripping.

NOTE 4 For RCCBs having a degree of protection higher than IP20 special constructions may be required.

Particular requirements are necessary for

- residual current operated circuit-breakers with integral overcurrent protection (see IEC 61009-1);
- RCCBs incorporated in or intended only for association with plugs and socket-outlets or with appliance couplers for household or similar general purposes;
- RCCBs intended to be used at frequencies other than 50 Hz or 60 Hz.

NOTE 5 For the time being, for RCCBs incorporated in, or intended only for socket-outlets or plugs, the requirements of this standard in conjunction with the requirements of IEC 60884-1 may be used as far as applicable.

NOTE 6 In DK, plugs and socket-outlets shall be in accordance with the requirements of the heavy current regulations, section 107.

NOTE 7 In the UK, the plug part of an RCCB shall comply with BS 1363-1 and the socket-outlet part(s) of an RCCB should comply with BS 1363-2. In the UK, the plug part and the socket-outlet part(s) of an RCCB need not comply with any IEC 60884-1 requirements.

The requirements of this standard apply for normal environmental conditions (see 7.1). Additional requirements may be necessary for RCCBs used in locations having severe environmental conditions.

RCCBs including batteries are not covered by this standard.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60038, *IEC standard voltages*

IEC 60051 (all parts), *Direct acting indicating analogue electrical measuring instruments and their accessories*

IEC 60060-1:1989, *High-voltage test techniques – Part 1: General definitions and test requirements*

IEC 60060-2:1994, *High-voltage test techniques – Part 2: Measuring systems*

IEC 60068-2-30:2005, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 h + 12 h cycle)*

IEC 60068-3-4: 2001, *Environmental testing – Part 3-4: Supporting documentation and guidance – Damp heat tests*

IEC 60112:2003, *Method for the determination of the proof and the comparative tracking indices of solid insulating materials*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60364-4-44:2007, *Low-voltage electrical installations – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*

IEC 60364-5-53:2001, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60417, *Graphical symbols for use on equipment*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60664-1:2007, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60695-2-10:2000, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60884-1, *Plugs and socket-outlets for household and similar purposes – Part 1: General requirements*

IEC 61009-1, *Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs) – Part 1: General rules*

IEC 61543:1995, *Residual current-operated protective devices (RCDs) for household and similar use – Electromagnetic compatibility*

CISPR 14-1:2005, *Electromagnetic compatibility – Requirements for household appliances, electric tools and similar apparatus – Part 1: Emission*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

Where the terms "voltage" or "current" are used, they imply r.m.s. values, unless otherwise specified.

NOTE For a glossary of symbols see Annex IB.

3.1 Definitions relating to currents flowing from live parts to earth

3.1.1

earth fault current

current flowing to earth due to an insulation fault

3.1.2

earth leakage current

current flowing from the live parts of the installation to earth in the absence of an insulation fault

3.1.3

pulsating direct current

current of pulsating wave form which assumes, in each period of the rated power frequency, the value 0 or a value not exceeding 0,006 A d.c. during one single interval of time, expressed in angular measure, of at least 150°

3.1.4

current delay angle α

time, expressed in angular measure, by which the starting instant of current conduction is delayed by phase control

3.2 Definitions relating to the energization of a residual current circuit-breaker

3.2.1

energizing quantity

electrical excitation quantity which alone, or in combination with other such quantities, shall be applied to an RCCB to enable it to accomplish its function under specified conditions