

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Low-voltage electrical installations –
Part 5-53: Selection and erection of electrical equipment – Devices
for protection for safety, isolation, switching, control and monitoring**

**Installations électriques à basse tension –
Partie 5-53: Choix et mise en oeuvre des matériels électriques – Dispositifs
de protection pour assurer la sécurité, le sectionnement, la coupure,
la commande et la surveillance**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2020 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and definitions clause of IEC publications issued between 2002 and 2015. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

67 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et définitions des publications IEC parues entre 2002 et 2015. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Low-voltage electrical installations –
Part 5-53: Selection and erection of electrical equipment – Devices
for protection for safety, isolation, switching, control and monitoring**

**Installations électriques à basse tension –
Partie 5-53: Choix et mise en oeuvre des matériels électriques – Dispositifs
de protection pour assurer la sécurité, le sectionnement, la coupure,
la commande et la surveillance**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.130.01; 91.140.50

ISBN 978-2-8322-9201-3

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

REDLINE VERSION

VERSION REDLINE



Low-voltage electrical installations –

**Part 5-53: Selection and erection of electrical equipment – Devices
for protection for safety, isolation, switching, control and monitoring**

Installations électriques à basse tension –

**Partie 5-53: Choix et mise en oeuvre des matériels électriques – Dispositifs
de protection pour assurer la sécurité, le sectionnement, la coupure,
la commande et la surveillance**

CONTENTS

FOREWORD	6
530.1 Scope	8
530.2 Normative references	8
530.3 Terms and definitions	11
530.4 General and common requirements	14
530.5 Erection of equipment	14
531 Devices for protection against indirect contact by automatic disconnection of supply	16
531.1 Overcurrent protective devices	16
531.1.1 TN systems	16
531.1.2 TT systems	17
531.1.3 IT systems	17
531.2 Residual current protective devices	19
531.2.1 General conditions of installation	19
531.2.2 Selection of devices according to their method of application	19
531.2.3 TN systems	19
531.2.4 TT systems	19
531.2.5 IT systems	19
531.3 Insulation monitoring devices	19
531 Equipment for protection against electric shock	16
531.1 General	16
531.2 Devices for automatic disconnection of supply	17
531.2.1 General	17
531.2.2 Overcurrent protective devices	17
531.2.3 Residual current protective devices	19
531.3 Equipment for protection by double or reinforced insulation	22
531.4 Equipment for protection by electrical separation	24
531.5 Equipment for protection by extra-low-voltage provided by SELV and PELV systems	24
531.5.1 Sources for SELV or PELV systems	24
531.5.2 Selection of plugs and socket-outlets	24
531.6 Devices for additional protection	24
531.7 Monitoring devices	25
532 Devices and precautions for protection against thermal effects	25
532.1 General	25
532.2 Locations with a particular risk of fire	25
532.2.1 General	25
532.2.2 Locations with external influences BD2, BD3 or BD4	25
532.2.3 Locations with external influences BE2	26
532.3 Selection of arc fault detection devices (AFDD)	26
533 Devices for protection against overcurrent	27
533.1 General requirements	27
533.1.1 General	27
533.1.2 Compliance with standards	27
533.1.3 Fuses	28
533.2 Selection of devices for protection against overload current	28

533.2.1	General	28
533.2.2	Presence of harmonic currents	29
533.2.3	Unequal current sharing between parallel conductors	29
533.3	Selection of devices for protection against short-circuit current	29
533.3.1	Thermal stresses	29
533.3.2	Breaking capacity	30
533.4	Positioning of overcurrent protection devices	30
533.4.1	General	30
533.4.2	Positioning of devices for overload protection	30
533.4.3	Positioning of devices for short-circuit protection	31
533.5	Co-ordination of overload and short-circuit protective functions	32
533.5.1	Protective functions provided by one device	32
533.5.2	Protective functions provided by separate devices	32
534	Devices for protection against transient overvoltages	32
534.1	General	32
534.2	Void	33
534.3	Void	33
534.4	Selection and erection of SPDs	33
534.4.1	SPD location and SPD test class	33
534.4.2	Transient overvoltage protection requirements	34
534.4.3	Connection types	34
534.4.4	Selection of SPDs	36
534.4.5	Protection of the SPD against overcurrent	40
534.4.6	Fault protection	42
534.4.7	SPDs installation in conjunction with RCDs	43
534.4.8	Connections of the SPD	43
534.4.9	Effective protective distance of SPDs	45
534.4.10	Connecting conductors of SPDs	46
535	Co-ordination of protective devices	46
535.1	Selectivity between overcurrent protective devices	46
535.1.1	General	46
535.1.2	Partial selectivity	47
535.1.3	Full selectivity	47
535.1.4	Total selectivity	47
535.1.5	Enhanced selectivity	47
535.2	Co-ordination between residual current protective devices and OCPDs	48
535.3	Selectivity between residual current protective devices	48
535.4	Selectivity of RCD and OCPD	48
535.5	Combined short-circuit protection of OCPDs	48
536	Isolation and switching	49
536.2	Isolation	49
536.2.1	General	49
536.2.2	Devices for isolation	50
536.3	Switching-off for mechanical maintenance	51
536.3.1	General	51
536.3.2	Devices for switching-off for mechanical maintenance	51
536.4	Emergency switching	52
536.4.1	General	52
536.4.2	Devices for emergency switching-off	52

536.4.3	Devices for emergency stopping	53
536.5	Functional switching (control).....	53
536.5.1	General	53
536.5.2	Devices for functional switching	53
537	Monitoring	54
537.1	General.....	54
537.1.1	Monitoring devices.....	54
537.1.2	Selection of insulation monitoring devices (IMDs)	54
537.1.3	Selection of residual current monitoring devices (RCMs)	54
537.2	IT systems for continuity of supply	54
537.2.1	General	54
537.2.2	Insulation monitoring devices (IMDs)	55
537.2.3	Installation of IMDs.....	55
537.3	IT public distribution system.....	55
537.4	Off-line systems in TN, TT and IT systems.....	55
Annex A (informative)	Position of devices for overload protection	57
A.1	General.....	57
A.2	Cases where overload protection need not be placed at the origin of the branch circuit	57
Annex B (informative)	Position of devices for short-circuit protection	59
B.1	General.....	59
B.2	Cases where short-circuit protection need not be placed at the origin of branch circuit	59
Annex C (informative)	SPD installation – Examples of installation diagrams according to system configurations	61
C.1	TT system – 3 phase supply plus neutral	61
C.2	TN-C and TN-C-S systems – 3 phase supply	65
C.3	TN-S system – 3 phase supply plus neutral.....	69
C.4	IT system – 3 phase supply with or without neutral	71
Annex D (informative)	Installation supplied by overhead lines.....	74
Annex E (normative)	Reference standards for devices for isolation and switching.....	75
Annex F (informative)	List of notes concerning certain countries.....	77
Annex G (informative)	Description of the different types of residual current devices (RCDs)	86
Bibliography		90
Figure 1	– Example of installation of class I, class II and class III tested SPDs	34
Figure 2	– Connection type CT1 (4+0-configuration) for a three-phase system with neutral	35
Figure 3	– Connection type CT1 (3+0-configuration) for a three-phase system.....	35
Figure 4	– Connection type CT2 (e.g. 3+1-configuration) for a three-phase system with neutral	36
Figure 5	– Connection points of an SPD assembly	40
Figure 6	– Example of overcurrent protection in the SPD branch by using a dedicated external overcurrent protective device.....	41
Figure 7	– Protective device, which is a part of the installation, also used to protect the SPD	42
Figure 8	– Connection of the SPD	44

Figure 9 – Example of installation of an SPD in order to decrease lead length of SPD supply conductors	45
Figure 10 – Example of selectivity	47
Figure 11 – Example of currents and their correlation to selectivity	48
Figure 12 – Example of combined short-circuit protection of OCPDs	49
Figure A.1 – Overload protective device (P_2) not at the origin of branch circuit (B)	57
Figure A.2 – Overload protective device (P_2) installed within 3 m of the origin of the branch circuit (B)	58
Figure B.1 – Limited change of position of short-circuit protective device (P_2) on a branch circuit	59
Figure B.2 – Short-circuit protective device P_2 installed at a point on the supply side of the origin of a branch circuit	60
Figure C.1 – Example of SPDA installation with connexion type CT2 on the supply side (upstream) of the main RCD in TT system	61
Figure C.2 – Example of SPD installation with connexion type CT2 on the supply side (upstream) of the main RCD in TT system	62
Figure C.3 – Example of SPDA installation on the load side (downstream) of the main RCD in TT system	63
Figure C.4 – Example of SPD installation on the load side (downstream) of the RCD in TT system	64
Figure C.5 – Example of SPDA installation in TN-C system	65
Figure C.6 – Example of SPD installation with connexion type CT1 in TN-C system	66
Figure C.7 – Example of SPD installation in TN-C-S system where the PEN is separated into PE and N at the origin of the installation (upstream of the SPD)	67
Figure C.8 – Example of SPDs installation in TN-C-S in different distribution boards	68
Figure C.9 – Example of SPDA installation in TN-S system	69
Figure C.10 – Example of SPDs installation in TN-S	70
Figure C.11 – Example of SPDA installation in IT system with neutral	71
Figure C.12 – Example of SPD installation in IT system without neutral	72
Figure C.13 – Example of SPD installation in IT system with neutral	73
Figure F.1 – Single user	82
Figure F.2 – Several users	82
Figure F.3 – Lamp control circuit with switching in the neutral conductor	84
Figure G.1 – Possible earth fault currents in systems with semiconductors	89
Table 1 – Required rated impulse voltage of equipment	37
Table 2 – U_c of the SPD dependent on supply system configuration	38
Table 3 – Nominal discharge current (I_n) in kA depending on supply system and connection type	39
Table 4 – Selection of impulse discharge current (I_{imp}) where the building is protected against direct lightning strike	39
Table 5 – Connection of the SPD dependent on supply system	43
Table D.1 – Selection of impulse discharge current (I_{imp})	74
Table E.1 – Devices for isolation and switching	75

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE ELECTRICAL INSTALLATIONS –

Part 5-53: Selection and erection of electrical equipment – Devices for protection for safety, isolation, switching, control and monitoring

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.

IEC 60364-5-53 edition 4.1 contains the fourth edition (2019-02) [documents 64/2352/FDIS and 64/2359/RVD] and its amendment 1 (2020-12) [documents 64/2457/FDIS and 64/2465/RVD].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

International Standard IEC 60364 has been prepared by IEC technical committee 64: Electrical installations and protection against electric shock.

This fourth edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) revision of all clauses except 531 and 534;
- b) introduction of a new Clause 537 Monitoring;
- c) Clause 530 contains all normative references and all terms and definitions.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

The reader's attention is drawn to the fact that Annex F lists all of the “in-some-country” clauses on differing practices relating to the subject of this standard.

A list of all parts in the IEC 60364 series, published under the general title *Low-voltage electrical installations*, can be found on the IEC website.

The committee has decided that the contents of the base publication and its amendment will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

LOW-VOLTAGE ELECTRICAL INSTALLATIONS –

Part 5-53: Selection and erection of electrical equipment – Devices for protection for safety, isolation, switching, control and monitoring

530.1 Scope

This document provides requirements for:

- a) isolation, switching, control and monitoring, and
- b) selection and erection of:
 - 1) devices for isolation, switching, control and monitoring, and
 - 2) devices to achieve compliance with measures of protection for safety.

530.2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60204-1, *Safety of machinery – Electrical equipment of machines – Part 1: General requirements*

IEC 60269-2, *Low-voltage fuses – Part 2: Supplementary requirements for fuses for use by authorized persons (fuses mainly for industrial application) – Examples of standardized systems of fuses A to K*

IEC 60269-3, *Low-voltage fuses – Part 3: Supplementary requirements for fuses for use by unskilled persons (fuses mainly for household and similar applications) – Examples of standardized systems of fuses A to F*

IEC 60269-4, *Low-voltage fuses – Part 4: Supplementary requirements for use-links for the protection of semiconductor devices*

IEC 60309 (all parts), *Plugs, socket-outlets and couplers for industrial purposes*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*
IEC 60364-4-41:2005/AMD1:2017

IEC 60364-4-42:2010, *Low-voltage electrical installations – Part 4-42: Protection for safety – Protection against thermal effects*
IEC 60364-4-42:2010/AMD1:2014

IEC 60364-4-43:2008, *Low-voltage electrical installations – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-4-44:2007, *Low-voltage electrical installations – Part 4-44: Protection for safety – Protection against voltage disturbances and electromagnetic disturbances*
IEC 60364-4-44:2007/AMD1:2015

IEC 60364-5-55, *Electrical installations of buildings – Part 5-55: Selection and erection of electrical equipment – Other equipment*

IEC 60364-6:2016, *Low voltage electrical installations– Part 6: Verification*

IEC 60417 (all parts), *Graphical symbols for use on equipment*

IEC 60664-1:2007, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60669-1, *Switches for household and similar fixed-electrical installations – Part 1: General requirements*

IEC 60669-2-1, *Switches for household and similar fixed electrical installations – Part 2-1: Particular requirements – Electronic switches*

IEC 60669-2-2, *Switches for household and similar fixed electrical installations – Part 2-2: Particular requirements – Electromagnetic remote-control switches (RCS)*

IEC 60669-2-3, *Switches for household and similar fixed electrical installations – Part 2-3: Particular requirements – Time-delay switches (TDS)*

IEC 60669-2-4, *Switches for household and similar fixed electrical installations – Part 2-4: Particular requirements – Isolating switches*

IEC 60669-2-5, *Switches for household and similar fixed electrical installations – Part 2-5: Particular requirements – Switches and related accessories for use in home and building electronic systems (HBES)*

IEC 60669-2-6, *Switches for household and similar fixed electrical installations – Part 2-6: Particular requirements – Fireman's switches for exterior and interior signs and luminaires*

IEC 60670-24, *Boxes and enclosures for electrical accessories for household and similar fixed electrical installations – Part 24: Particular requirements for enclosures for housing protective devices and other power dissipating electrical equipment*

IEC 60884 (all parts), *Plugs and socket-outlets for household and similar purposes*

IEC 60898 (all parts), *Electrical accessories – Circuit-breakers for overcurrent protection for household and similar installations*

IEC 60906 (all parts), *IEC system of plugs and socket-outlets for household and similar purposes*

IEC 60947-2:2016, *Low-voltage switchgear and controlgear – Part 2: Circuit-breakers*

IEC 60947-3, *Low-voltage switchgear and controlgear – Part 3: Switches, disconnectors, switch-disconnectors and fuse-combination units*

IEC 60947-4-1, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 60947-4-2, *Low-voltage switchgear and controlgear – Part 4-2: Contactors and motor-starters – AC semiconductor motor controllers and starters*

IEC 60947-4-3, *Low-voltage switchgear and controlgear – Part 4-3: Contactors and motor-starters – AC semiconductor controllers and contactors for non-motor loads*

IEC 60947-5-1, *Low-voltage switchgear and controlgear – Part 5-1: Control circuit devices and switching elements – Electromechanical control circuit devices*

IEC 60947-6-1, *Low-voltage switchgear and controlgear – Part 6-1: Multiple function equipment – Transfer switching equipment*

IEC 60947-6-2, *Low-voltage switchgear and controlgear – Part 6-2: Multiple function equipment – Control and protective switching devices (or equipment) (CPS)*

IEC 61008 (all parts), *Residual current operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs)*

IEC 61009 (all parts), *Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs)*

IEC 61095, *Electromechanical contactors for household and similar purposes*

IEC 61439-2, *Low-voltage switchgear and controlgear assemblies – Part 2: Power switchgear and controlgear assemblies*

IEC 61439-3, *Low-voltage switchgear and controlgear assemblies – Part 3: Distribution boards intended to be operated by ordinary persons (DBO)*

IEC 61439-6, *Low-voltage switchgear and controlgear assemblies – Part 6: Busbar trunking systems (busways)*

IEC 61534 (all parts), *Powertrack systems*

IEC 61557-8, *Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 8: Insulation monitoring devices for IT systems*

IEC 61557-9, *Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 9: Equipment for insulation fault location in IT systems*

IEC 61643-11, *Low-voltage surge protective devices – Part 11: Surge protective devices connected to low-voltage power systems – Requirements and test methods*

IEC 61643-12, *Low-voltage surge protective devices – Part 12: Surge protective devices connected to low-voltage power distribution systems – Selection and application principles*

IEC 61984:2008, *Connectors – Safety requirements and tests*

IEC 61995 (all parts), *Devices for the connection of luminaires for household and similar purposes*

IEC 62020, *Electrical accessories – Residual current monitors for household and similar uses (RCMs)*

IEC 62208, *Empty enclosures for low-voltage switchgear and controlgear assemblies – General requirements*

IEC 62305 (all parts), *Protection against lightning*

IEC 62423, *Type F and type B residual current operated circuit-breakers with and without integral overcurrent protection for household and similar uses*

IEC 62606, *General requirements for arc fault detection devices*

IEC 62626-1, *Low-voltage switchgear and controlgear enclosed equipment – Part 1: Enclosed switch-disconnectors outside the scope of IEC 60947-3 to provide isolation during repair and maintenance work*

530.3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>.

530.3.1

disconnector

mechanical switching device which in the open position complies with the requirements specified for the isolating function

Note 1 to entry: A disconnector is capable of opening and closing a circuit when either negligible current is broken or made, or when no significant change in the voltage across the terminals of each of the poles of the disconnector occurs. It is also capable of carrying currents under normal circuit conditions and carrying for a specified time currents under abnormal conditions such as those of short-circuit.

[SOURCE: IEC 60050-441:2000, 441-14-05, modified – Referring to isolating function instead of isolating distance.]

530.3.2

switch disconnector

switch which, in the open position, satisfies the isolating requirements specified for a disconnector

[SOURCE: IEC 60050-441:1984, 441-14-12]

530.3.3

mechanical switch

device capable of making, carrying and breaking currents through contacts controlled by mechanical operation under normal circuit conditions which may include specified operating overload conditions and also carrying for specified time currents under specified abnormal circuit conditions such as those of short-circuit

Note 1 to entry: A switch can be capable of making but not breaking short-circuit currents.

[SOURCE: IEC 60050-441:2000, 441-14-10, modified – "through contacts controlled by mechanical operation" has been added.]

530.3.4

switching-off for mechanical maintenance

opening operation of a switching device intended to inactivate an item or items of electrically powered equipment for the purpose of preventing a hazard, other than due to electric shock or to arcing, during non-electrical work on the equipment