

TECHNICAL SPECIFICATION



**Rotating electrical machines –
Part 25: AC electrical machines used in power drive systems – Application guide**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2022 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

Preview generated by EVS

TECHNICAL SPECIFICATION



**Rotating electrical machines –
Part 25: AC electrical machines used in power drive systems – Application guide**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.160.01

ISBN 978-2-8322-3957-5

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	9
INTRODUCTION	11
1 Scope	12
2 Normative references	12
3 Terms and definitions	13
4 System characteristics	16
4.1 General	16
4.2 System information	16
4.3 Torque/speed considerations	17
4.3.1 General	17
4.3.2 Torque/speed capability	17
4.3.3 Electrical machine rating	20
4.3.4 Limiting factors on torque/speed capability	20
4.3.5 Safe operating speed, over-speed capability and over-speed test	20
4.3.6 Cooling arrangement	20
4.3.7 Voltage/frequency characteristics	21
4.3.8 Resonant speed bands	22
4.3.9 Duty cycles	22
4.4 Electrical machine requirements	23
5 Losses and their effects (for induction electrical machines fed from voltage source converters)	26
5.1 General	26
5.2 Location of the additional losses due to converter supply and ways to reduce them	27
5.3 Converter features to reduce the electrical machine losses	28
5.3.1 Reduction of fundamental losses	28
5.3.2 Reduction of additional losses due to converter supply	28
5.4 Use of filters to reduce additional electrical machine losses due to converter supply	29
5.5 Temperature influence on life expectancy	29
5.6 Determination of electrical machine efficiency	30
6 Acoustic noise, vibration and torsional oscillation	30
6.1 Acoustic noise	30
6.1.1 General	30
6.1.2 Changes in noise emission due to changes in speed	30
6.1.3 Magnetically excited noise	31
6.1.4 Sound power level determination and limits	33
6.2 Vibration (excluding torsional oscillation)	33
6.2.1 General	33
6.2.2 Vibration level determination and limits	34
6.3 Torsional oscillation	34
7 Electrical machine insulation electrical stresses	35
7.1 General	35
7.2 Causes	35
7.3 Winding electrical stress	37
7.4 Limits and responsibility	38

7.4.1	Electrical machines design for low voltage ($\leq 1\,000\text{ V}$)	38
7.4.2	Electrical machines designed for medium and high voltage ($> 1\,000\text{ V}$)	39
7.5	Methods of reduction of voltage stress	40
7.6	Insulation stress limitation	40
8	Bearing currents	41
8.1	Sources of bearing currents in converter-fed electrical machines motors	41
8.1.1	General	41
8.1.2	Circulating currents due to magnetic asymmetry	41
8.1.3	Electrostatic build-up	41
8.1.4	High-frequency voltages effects in converter operation	41
8.2	Generation of high-frequency bearing currents	42
8.2.1	General	
8.2.2	Circulating current	
8.2.3	Shaft earthing current	
8.2.4	Capacitive discharge current	
8.2.1	Common mode voltage	44
8.2.2	Motor HF equivalent circuit and the resulting bearing current types	45
8.2.3	Circulating current	47
8.2.4	Rotor ground current	48
8.2.5	Electrostatic Discharge Machining (EDM) currents	49
8.3	Common mode circuit	
8.3.1	General	
8.3.2	System common mode current flow	
8.3	Consequences of excessive bearing currents	51
8.4	Stray capacitances	
8.4.1	General	
8.4.2	Major component of capacitance	
8.4.3	Other capacitances	
8.4	Preventing high-frequency bearing current damage	58
8.4.1	Basic approaches	58
8.4.2	Other preventive measures	58
8.4.3	Other factors and features influencing the bearing currents	61
8.5	Additional considerations for electrical machines motors fed by high voltage source converters	62
8.5.1	General	62
8.5.2	Bearing protection of cage induction, brushless synchronous and permanent magnet electrical machines motors	62
8.5.3	Bearing protection for slip-ring electrical machines motors and for synchronous electrical machines motors with brush excitation	62
8.6	Bearing current protection for electrical machines motors fed by high-voltage current source converters	62
9	Installation	62
9.1	Earthing, bonding and cabling	62
9.1.1	General	62
9.1.2	Earthing	63
9.1.3	Bonding of electrical machines	63
9.1.4	Electrical machine power cables for high switching frequency converters	64
9.2	Reactors and filters	69
9.2.1	General	69

9.2.2	Output reactors	69
9.2.3	Voltage limiting filter (du/dt filter).....	69
9.2.4	Sinusoidal filter	69
9.2.5	Electrical machine termination unit.....	69
9.3	Power factor correction	70
9.4	Integral electrical machines (integrated electrical machine and drive modules)	71
10	Additional considerations for permanent magnet (PM) synchronous electrical machines fed by voltage source converters	71
10.1	System characteristics	71
10.2	Losses and their effects	71
10.3	Noise, vibration and torsional oscillation.....	72
10.4	Electrical machine insulation electrical stresses.....	72
10.5	Bearing currents	72
10.6	Particular aspects of permanent magnets	72
11	Additional considerations for cage induction electrical machines fed by high voltage source converters	72
11.1	General	72
11.2	System characteristics	73
11.3	Losses and their effects	74
11.3.1	Additional losses in the stator and rotor winding	74
11.3.2	Measurement of additional losses	74
11.4	Noise, vibration and torsional oscillation.....	74
11.5	Electrical machine insulation electrical stresses.....	75
11.5.1	General.....	75
11.5.2	Electrical machine terminal overvoltage.....	75
11.5.3	Stator winding voltage stresses in converter applications	75
11.6	Bearing currents	77
12	Additional considerations for synchronous electrical machines fed by voltage source converters	77
12.1	System characteristics	77
12.2	Losses and their effects	77
12.3	Noise, vibration and torsional oscillation.....	77
12.4	Electrical machine insulation electrical stresses.....	77
12.5	Bearing currents	78
13	Additional considerations for cage induction electrical machines fed by block-type current source converters	78
13.1	System characteristics (see Figure 35 and Figure 36).....	78
13.2	Losses and their effects	79
13.3	Noise, vibration and torsional oscillation.....	81
13.4	Electrical machine insulation electrical stresses.....	81
13.5	Bearing currents	81
13.6	Additional considerations for six-phase cage induction electrical machines.....	82
14	Additional considerations for synchronous electrical machines fed by LCI	82
14.1	System characteristics	82
14.2	Losses and their effects	84
14.3	Noise, vibration and torsional oscillation.....	84
14.4	Electrical machine insulation electrical stresses.....	84
14.5	Bearing currents	84

15	Additional considerations for cage induction electrical machines fed by pulsed current source converters (PWM CSI)	84
15.1	System characteristics (see Figure 39)	84
15.2	Losses and their effects	85
15.3	Noise, vibration and torsional oscillation	85
15.4	Electrical machine insulation electrical stresses	85
15.5	Bearing currents	86
16	Wound rotor induction (asynchronous) electrical machines supplied by voltage source converters in the rotor circuit	86
16.1	System characteristics	86
16.2	Losses and their effects	86
16.3	Noise, vibration and torsional oscillation	86
16.4	Electrical machine insulation electrical stresses	86
16.5	Bearing currents	86
17	Other electrical machine/converter systems	87
17.1	Drives supplied by cyclo-converters	87
17.2	Wound rotor induction (asynchronous) electrical machines supplied by current source converters in the rotor circuit	88
18	Special consideration for standard fixed-speed induction electrical machines in the scope of IEC 60034-12 when fed from voltage source converter and motor requirements to be considered a converter capable motor	89
18.1	General	89
18.2	Torque derating during converter operation	90
18.2.1	General	90
18.2.2	Self-cooled motors	91
18.2.3	Non self-cooled motors	92
18.3	Losses and their effects	92
18.4	Noise, vibrations and torsional oscillation	92
18.5	Electrical machine insulation electrical stresses	92
18.5.1	General	92
18.5.2	Converter capable motor	93
18.6	Bearing currents in converter capable motors	94
18.7	Speed range mechanical limits	95
18.7.1	General	95
18.7.2	Maximum safe operating speed	95
18.7.3	Minimum speed	95
18.8	Overload torque capability	96
18.9	Excess overload current limits	96
18.9.1	General	96
18.9.2	Converter capable motor	96
18.10	Volts/Hz ratio and voltage boost	96
18.11	Resonance	96
18.12	Hazardous area operation	97
18.12.1	General	97
18.12.2	Converter capable motor	97
18.13	Unusual service conditions	98
18.13.1	Converter capable motors	98
18.13.2	Unusual converter-fed applications	98
19	Additional considerations for synchronous reluctance electrical machine fed by voltage source converters	98

19.1	System characteristics.....	98
19.2	Losses and their effects.....	98
19.3	Noise, vibration and torsional oscillation.....	99
19.4	Electrical machine insulation electrical stresses.....	99
19.5	Bearing currents.....	99
19.6	Particular aspects of synchronous reluctance electrical machines.....	99
Annex A	(informative) Converter characteristics.....	100
A.1	Converter control types.....	100
A.1.1	General.....	100
A.1.2	Converter type considerations.....	101
A.2	Converter output voltage generation (for voltage source converters).....	101
A.2.1	Pulse width modulation (PWM).....	101
A.2.2	Hysteresis (sliding mode).....	102
A.2.3	Influence of switching frequency.....	102
A.2.4	Multi-level converters.....	103
A.2.5	Parallel converter operation.....	104
Annex B	(informative) Output characteristics of 2 level voltage source converter spectra.....	105
Annex C	(informative) Voltages to be expected at the power interface between converter and electrical machine.....	109
Annex D	(informative) Speed and harmonic capability of converter capable induction motor.....	113
D.1	General.....	113
D.2	Harmonic capability of converter capable motors.....	113
D.3	Speed capability and derating in variable torque application.....	114
D.4	Speed capability and derating in a constant torque application.....	114
Bibliography	116
List of comments	117
Figure 1	– Torque/speed capability.....	18
Figure 2	– Converter output current.....	19
Figure 2	– Current required by motor.....	19
Figure 3	– Examples of possible converter output voltage/frequency characteristics.....	22
Figure 4	– Example for the dependence of the electrical machine losses caused by harmonics P_h , related to the losses P_{f1} at operating frequency f_1 , on the switching frequency f_s in case of 2 level voltage source converter supply.....	27
Figure 5	– Example of measured losses P_L as a function of frequency f and supply type.....	28
Figure 6	– Additional losses ΔP_L of an electrical machine (same electrical machine as Figure 5) due to converter supply, as a function of pulse frequency f_p , at 50 Hz rotational frequency.....	29
Figure 7	– Relative fan noise as a function of fan speed.....	31
Figure 8	– Vibration modes of the stator core.....	32
Figure 9	– Typical surges at the terminals of an electrical machine fed from a PWM converter.....	35
Figure 10	– Typical voltage surges on one phase at the converter and at the electrical machine terminals (2 ms/division).....	36
Figure 11	– Individual short rise-time surge from Figure 10 (1 μ s/division).....	36

Figure 12 – Definition of the rise-time t_r of the voltage pulse at the electrical machine terminals.....	37
Figure 13 – First turn voltage as a function of the rise-time.....	38
Figure 14 – Discharge pulse occurring as a result of converter generated voltage surge at electrical machine terminals (100 ns/division).....	40
Figure 15 – Possible bearing currents.....	41
Figure 16 – Electrical machine capacitances.....	42
Figure 17 – Bearing pitting due to electrical discharge (pit diameter 30 μm to 50 μm).....	43
Figure 18 – Fluting due to excessive bearing current.....	44
Figure 15 – Classification of bearing currents.....	41
Figure 16 – Parasitic impedances to earth of drive system components	42
Figure 17 – Common mode voltage a) determination b) waveform example.....	45
Figure 18 – HF equivalent circuit diagram (a) of a motor (b) geometrical representation of capacitances.....	46
Figure 19 – Graphical representation of the different high frequency bearing current types in the drive unit highlighting the involved physical components.....	47
Figure 20 – Principle of circulating currents formation	48
Figure 21 – Rotor ground current principle	49
Figure 22 – Example of measured EDM-current pulses for a 400 V and 500 kW induction motor in converter operation	50
Figure 23 – Photographs of damaged motor bearings.....	53
Figure 24 – Bonding strap from electrical machine terminal box to electrical machine frame.....	64
Figure 25 – Examples of shielded electrical machine cables and connections	65
Figure 26 – Parallel symmetrical cabling of high-power converter and electrical machine.....	66
Figure 27 – Converter connections with 360° HF cable glands showing the Faraday cage	67
Figure 28 – Electrical machine end termination with 360° connection.....	67
Figure 29 – Cable shield connection	68
Figure 30 – Characteristics of preventative measures.....	70
Figure 31 – Schematic of typical three-level converter.....	73
Figure 32 – Output voltage and current from typical three-level converter	73
Figure 33 – Typical first turn voltage ΔU (as a percentage of the line-to-ground voltage) as a function of du/dt	75
Figure 34 – Medium-voltage and high-voltage form-wound coil insulating and voltage stress control materials	76
Figure 35 – Schematic of block-type current source converter	78
Figure 36 – Current and voltage waveforms of block-type current source converter.....	78
Figure 37 – Influence of converter supply on the losses of a cage induction electrical machine (frame size 315 M, design N) with rated values of torque and speed	80
Figure 38 – Schematic and voltage and current waveforms for a synchronous electrical machine supplied from a current source converter.....	83
Figure 39 – Schematic of pulsed current source converter.....	84
Figure 40 – Limiting curve of admissible impulse voltage \hat{U}_{LL}/U_N (peak value of line to line voltage including voltage reflection and damping/rated voltage) at the electrical machine terminals as a function of the rise-time t_r.....	85

Figure 40 – Voltages and currents of pulsed current source converter.....	85
Figure 41 – Schematic of cyclo-converter.....	87
Figure 42 – Voltage and current waveforms of a cyclo-converter.....	87
Figure 43 – Diagram comparing converter capable motor to converter duty motor	89
Figure 44 – Fundamental voltage U_1 as a function of operating frequency f_1	90
Figure 45 – Torque derating factor for cage induction electrical machines of design N, IC 0141411 (self-circulating cooling) as a function of operating frequency f_1 (example).....	91
Figure A.1 – Effects of switching frequency on electrical machine and converter losses	102
Figure A.2 – Effects of switching frequency on acoustic noise.....	103
Figure A.3 – Effects of switching frequency on torque ripple	103
Figure B.1 – Waveform of line-to-line voltage U_{LL} for voltage source converter supply with switching frequency $f_s = 30 \times f_1$ (example)	105
Figure B.2 – Typical output voltage frequency spectra of converter output voltage for a constant frequency PWM control versus hysteresis control	106
Figure B.3 – Typical output voltage frequency spectra of converter output voltage for random frequency PWM versus hysteresis control.....	106
Figure B.4 – Typical spectra of converter output voltage frequency spectra for a two- phase modulated control versus hysteresis modulation.....	107
Figure B.5 – Typical time characteristics of electrical machine current for a Constant frequency PWM control versus hysteresis control.....	107
Figure B.6 – Typical time characteristics of electrical machine current for a two-phase modulated control versus hysteresis modulation.....	108
Figure C.1 – Example of typical voltage curves and parameters of a two level inverter versus time at the electrical machine terminals (phase to phase voltage; taken from IEC TS 61800-8)	109
Figure D.1 – Derating curve for harmonic voltages	114
Figure D.2 – Torque capability at reduced speeds due to the effects of reduced cooling (applies to 50 Hz or 60 Hz design N).....	115
Table 1 – Significant factors affecting torque/speed capability	20
Table 2 – Electrical machine design considerations.....	24
Table 3 – Electrical machine parameters for the tuning of the converter.....	25
Table 4 – Operating voltage at the terminals in units of U_N where the electrical machines may operate reliably without special agreements between manufacturers and system integrators.....	39
Table 5 – Different grades of roller bearing damages	54
Table 6 – Effectiveness of bearing current counter measures	59

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ROTATING ELECTRICAL MACHINES –

Part 25: AC electrical machines used in power drive systems – Application guide

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This commented version (CMV) of the official standard IEC TS 60034-25:2022 edition 4.0 allows the user to identify the changes made to the previous IEC TS 60034-25:2014 edition 3.0. Furthermore, comments from IEC TC 2 experts are provided to explain the reasons of the most relevant changes, or to clarify any part of the content.

A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text. Experts' comments are identified by a blue-background number. Mouse over a number to display a pop-up note with the comment.

This publication contains the CMV and the official standard. The full list of comments is available at the end of the CMV.

IEC TS 60034-25 has been prepared by IEC technical committee 2: Rotating machinery. It is a Technical Specification.

This fourth edition of IEC TS 60034-25 cancels and replaces the third edition, published in 2014.

This edition includes the following significant technical changes with respect to the previous edition: 1

- a) The definitions of a converter capable motor and a converter duty motor are added.
- b) Clause 18 modified to include the performance expectations of a converter capable motor.
- c) Clause 8 modified to update shaft currents section.
- d) Annex D added to define the derating requirements.

The text of this Technical Specification is based on the following documents:

Draft	Report on voting
2/2067/DTS	2/2097/RVDTS

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Specification is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 60034 series, published under the general title *Rotating electrical machines*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The performance characteristics and operating data for converter-fed electrical machines are influenced by the complete drive system, comprising supply system, converter, cabling, electrical machine, mechanical shafting and control equipment. Each of these components exists in numerous technical variants. Any values quoted in this document are thus indicative only.

In view of the complex technical interrelations within the system and the variety of operating conditions, it is beyond the scope and object of this document to specify numerical or limiting values for all the quantities which are of importance for the design of the power drive system.

To an increasing extent, it is the practice that power drive systems consist of components produced by different manufacturers. The object of this document is to explain, as far as possible, the influence of these components on the design of the electrical machine and its performance characteristics.

This document deals with both AC electrical machines which are specifically designed for converter supply and converter-fed electrical machines within the scope of IEC 60034-12, which are designed originally for mains supply.

ROTATING ELECTRICAL MACHINES –

Part 25: AC electrical machines used in power drive systems – Application guide

1 Scope

This part of IEC 60034 describes the performance characteristics of AC electrical machines for use on converter supplies. For electrical machines specifically designed for converter duty application design features are defined. It also specifies the interface parameters and interactions between the electrical machine and the converter including installation guidance as part of a power drive system, but except for the voltage at the power interface which is described in IEC TS 61800-8.

The general requirements of relevant parts of the IEC 60034 series of standards also apply to electrical machines within the scope of this document.

For electrical machines operating in potentially explosive atmospheres, additional requirements as described in the IEC 60079 series ~~or IEC 61241 series~~ for dust ignition proof apply.

This document is not primarily concerned with safety. However, some of its recommendations may have implications for safety, which ~~should be~~ are considered as necessary.

Where a converter manufacturer provides specific installation recommendations, they ~~should~~ take precedence over the recommendations of this document.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-1:2010/2022, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60034-2-1, *Rotating electrical machines – Part 2-1: Standard methods for determining losses and efficiency from tests (excluding machines for traction vehicles)*

IEC 60034-2-2, *Rotating electrical machines – Part 2-2: Specific methods for determining separate losses of large machines from tests – Supplement to IEC 60034-2-1*

IEC 60034-2-3, *Rotating electrical machines – Part 2-3: Specific test methods for determining losses and efficiency of converter-fed AC induction motors*

IEC 60034-6, *Rotating electrical machines – Part 6: Methods of cooling (IC Code)*

IEC 60034-9:2003/2021, *Rotating electrical machines – Part 9: Noise limits*
~~Amendment 1:2007~~

IEC 60034-12, *Rotating electrical machines – Part 12: Starting performance of single-speed three-phase cage induction motors*

IEC 60034-14:~~2003~~2018, *Rotating electrical machines – Part 14: Mechanical vibration of certain machines with shaft heights 56 mm and higher – Measurement, evaluation and limits of vibration severity*

~~Amendment 1:2007~~

IEC ~~TS~~ 60034-18-41:2014, *Rotating electrical machines – Part 18-41: Partial discharge free electrical insulation systems (Type I) used in rotating electrical machines fed from voltage converters – Qualification and quality control tests*

IEC 60034-18-41:2014/AMD1:2019

IEC ~~TS~~ 60034-18-42:2017, *Rotating electrical machines – Part 18-42: ~~Qualification and acceptance tests for~~ Partial discharge resistant electrical insulation systems (Type II) used in rotating electrical machines fed from voltage converters – Qualification tests*

IEC 60034-18-42:2017/AMD1:2020

~~IEC 60050 – (all parts): International Electrotechnical Vocabulary (available at <http://www.electropedia.org>)~~

IEC 60079 (all parts): *Explosive atmospheres*

IEC 60079-7, *Explosive atmospheres – Part 7: Equipment protection by increased safety "e"*

IEC TR 61000-5-1, *Electromagnetic compatibility (EMC) – Part 5: Installation and mitigation guidelines – Section 1: General considerations – Basic EMC publication*

IEC TR 61000-5-2, *Electromagnetic compatibility (EMC) – Part 5: Installation and mitigation guidelines – Section 2: Earthing and cabling*

~~IEC 61800-2:1998, Adjustable speed electrical power drive systems – Part 2: General requirements – Rating specifications for low voltage adjustable frequency a.c. power drive systems~~

IEC 61800-3, *Adjustable speed electrical power drive systems – Part 3: EMC requirements and specific test methods*

IEC 61800-5-1, *Adjustable speed electrical power drive systems – Part 5-1: Safety requirements – Electrical, thermal and energy*

IEC TS 61800-8:2010, *Adjustable speed electrical power drive systems – Part 8: Specification of voltage on the power interface*

IEC TS 62578:~~2009~~2015, *Power electronics systems and equipment – Operation conditions and characteristics of active infeed converter (AIC) applications including design recommendations for their emission values below 150 kHz*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>