
ICS 29.160

English Version

**Rotating electrical machines - Part 18-41: Partial discharge free electrical insulation systems (Type I) used in electrical rotating machines fed from voltage converters - Qualification and quality control tests
(IEC 60034-18-41:2014/A1:2019/COR1:2020)**

Machines électriques tournantes - Partie 18-41: Systèmes d'isolation électrique sans décharge partielle (Type I) utilisés dans des machines électriques tournantes alimentées par des convertisseurs de tension - Essais de qualification et de contrôle qualité
(IEC 60034-18-41:2014/A1:2019/COR1:2020)

Drehende elektrische Maschinen - Teil 18-41: Qualifizierung und Qualitätsprüfungen für teilentladungsfreie elektrische Isoliersysteme (Typ I) in drehenden elektrischen Maschinen, die von Spannungsumrichtern gespeist werden
(IEC 60034-18-41:2014/A1:2019/COR1:2020)

This corrigendum becomes effective on 25 December 2020 for incorporation in the English language version of the EN.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

Endorsement notice

The text of the corrigendum IEC 60034-18-41:2014/A1:2019/COR1:2020 was approved by CENELEC as EN 60034-18-41:2014/A1:2019/AC:2020-12 without any modification.

INTERNATIONAL ELECTROTECHNICAL COMMISSION
 COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

IEC 60034-18-41
 Amendment 1 to Edition 1.0 2019-06

IEC 60034-18-41
 Amendement 1 à l'Édition 1.0 2019-06

ROTATING ELECTRICAL MACHINES –

MACHINES ÉLECTRIQUES TOURNANTES –

Part 18-41: Partial discharge free electrical insulation systems (Type I) used in rotating electrical machines fed from voltage converters – Qualification and quality control tests

Partie 18-41: Systèmes d'isolation électrique sans décharge partielle (Type I) utilisés dans des machines électriques tournantes alimentées par des convertisseurs de tension – Essais de qualification et de contrôle qualité

CORRIGENDUM 1

Corrections to the French version appear after the English text.

Les corrections à la version française sont données après le texte anglais.

12.2 Routine withstand voltage test

Replace the text of the third paragraph with the following new text:

During the routine testing of quantity produced machines up to 200 kW (or kVA) and rated for $U_N \leq 1$ kV, the 1 min test may be replaced by a test of 1 s (see IEC 60034-1) at 120 % of the test voltage specified in Table D.1, for example S – (manufacturer specified): $(TVF \cdot 2U_N + 1 \text{ kV}) \cdot 1,2$.

Table D.1 – Withstand test voltages according to IVIC for Type I insulation systems

Replace the table with the following new table:

IVIC	Maximum allowable peak to peak operating voltages in units of U_N^a		Maximum allowable enhancement ratio for the phase to ground peak to peak voltage	TVF	Examples of routine phase to ground test voltages for a machine with $U_N = 500$ V tested at 50/60 Hz according to IEC 60034-1 (kV r.m.s.)	
	Phase to phase	Phase to ground U_{IVIC} / U_N			Converter-fed (IVIC specified)	Line fed ^b
None (line)	2,8	1,6				2
A – Benign	3,0	2,1	1,3	0,7	2,0	2
B – Moderate	4,1	2,8	1,7	1,0	2,0	2
C – Severe	5,4	3,8	2,3	1,3	2,3	2

D – Extreme	6,7	4,7	2,9	1,7	2,7	2
S (manufacturer specified)	X	Y	$\frac{Y\sqrt{3}}{2\sqrt{2}}$	$\frac{Y}{2\sqrt{2}}$	$TVF \cdot 2U_N + 1 \text{ kV}$	2

- ^a These voltages are calculated using the formulae described in Clause B.5. The factor of 1,1 for the variation of the line voltage is not included.
- ^b The voltage in this column is the test voltage specified in IEC 60034-1 for $U_N = 500 \text{ V}$.

NOTE 1 Enhancement ratio is the maximum allowable phase to ground peak to peak voltage under converter-fed operation U_{IVIC} divided by the phase to ground peak to peak voltage under line operation $U_N / \sqrt{3} \cdot 2 / \sqrt{2}$.

NOTE 2 The values X and $Y = U_{IVIC} / U_N$ are independent and are chosen by the manufacturer.

NOTE 3 S is defined in Clause C.2.

NOTE 4 The test voltage is defined only by the maximum allowable peak to peak voltage at the motor terminals in operation. Other differences in the voltage waveform in operation are not taken into consideration.

NOTE 5 The equations in the line of IVIC "S" apply to the other IVICs A, B, C, D as well.