

**TUGEVVOOLUPAIGALDISED NIMIVAHELDUVPINGEGA
ÜLE 1KV JA ALALISPINGEGA ÜLE 1,5 KV.
OSA 1: VAHELDUVPINGE**

**Power installations exceeding 1 kV AC and 1,5 kV DC -
Part 1: AC (IEC 61936-1:2021)**

EESTI STANDARDI EESSÕNA**NATIONAL FOREWORD**

See Eesti standard EVS-EN IEC 61936-1:2021+A11:2026 sisaldab Euroopa standardi EN IEC 61936-1:2021 ja selle muudatuse A11:2025 ingliskeelset teksti.	This Estonian standard EVS-EN IEC 61936-1:2021+A11:2026 consists of the English text of the European standard EN IEC 61936-1:2021 and its amendment A11:2025.
Standard on jõustunud sellekohase teate avaldamisega EVS Teatajas. Euroopa standardimisorganisatsioonid on teinud Euroopa standardi rahvuslikele liikmetele kättesaadavaks 27.08.2021, muudatus A11 19.12.2025.	This standard has been endorsed with a notification published in the official bulletin of the Estonian Centre for Standardisation and Accreditation. Date of Availability of the European standard is 27.08.2021, for A11 19.12.2025.
Muudatusega A11 lisatud või muudetud teksti algus ja lõpp on tekstis tähistatud sümbolitega A11 A11 . Standard on kättesaadav Eesti Standardimis- ja Akrediteerimiskeskusest.	The start and finish of text introduced or altered by amendment A11 is indicated in the text by tags A11 A11 . The standard is available from the Estonian Centre for Standardisation and Accreditation.

Tagasisidet standardi sisu kohta on võimalik edastada, kasutades EVS-i veebilehel asuvat tagasiside vormi või saates e-kirja meiliaadressile standardiosakond@evs.ee.

ICS 29.020; 29.080.01

Standardite ja standardilaadsete dokumentide reprodutseerimise ja levitamise õigus kuulub Eesti Standardimis- ja Akrediteerimiskeskusele

Eesti standardid ja standardilaadsed dokumendid on Eesti Standardimis- ja Akrediteerimiskeskuse intellektuaalomand ning neid kasutatakse litsentsi alusel dokumentide kasutuslepingu tingimuste kohaselt.

Ilma Eesti Standardimis- ja Akrediteerimiskeskuse eelneva kirjaliku loata on keelatud standardite ja standardilaadsete dokumentide täielik või osaline reprodutseerimine, levitamine, muutmise või kasutamine mis tahes kujul ja viisil - sealhulgas kopeerimise, skaneerimise, salvestamise või jagamise teel digiplatvormidel (k.a masinõppe ja tehisintellekti rakendustes). Loata kasutamine väljaspool litsentsi tingimusi käsitletakse õigusrikkumisena.

Kui Teil on küsimusi standardite ja standardilaadsete dokumentide autoriõiguse kaitse kohta, võtke palun ühendust Eesti Standardimis- ja Akrediteerimiskeskusega:

Veebileht www.evs.ee; telefon +372 6055050; e-post info@evs.ee

The right to reproduce and distribute standards and standard-like documents belongs to the Estonian Centre for Standardisation and Accreditation

Estonian standards and standard-like documents are the intellectual property of the Estonian Centre for Standardisation and Accreditation and are made available under license in accordance with the terms and conditions of the document use agreement.

Without the prior written permission of the Estonian Centre for Standardisation and Accreditation, the full or partial reproduction, distribution, modification, or use of standards and standard-like documents in any form or by any means - including photocopying, scanning, storing, or sharing via digital platforms (incl. in machine learning and artificial intelligence applications) - is strictly prohibited. Any unauthorized use beyond the scope of the granted license is prohibited and may result in legal action.

If you have any questions about copyright, please contact Estonian Centre for Standardisation and Accreditation: Homepage www.evs.ee; phone +372 605 5050; e-mail info@evs.ee

English Version

**Power installations exceeding 1 kV AC and 1,5 kV DC - Part 1:
AC
(IEC 61936-1:2021)**

Installations électriques de puissance de tension supérieure
à 1 kV en courant alternatif et 1,5 kV en courant continu -
Partie 1: Courant alternatif
(IEC 61936-1:2021)

Starkstromanlagen mit Nennwechselspannungen über 1 kV
AC und 1,5 kV DC - Teil 1: Wechselstrom
(IEC 61936-1:2021)

This European Standard was approved by CENELEC on 2021-08-11. Amendment A11 was approved by CENELEC on 2025-12-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard and its amendment the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard and its Amendment A11 exist in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Türkiye and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

European foreword

The text of document 99/311/FDIS, future edition 3 of IEC 61936-1, prepared by IEC/TC 99 “Insulation co-ordination and system engineering of high voltage electrical power installations above 1,0 kV AC and 1,5 kV DC” was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN IEC 61936-1:2021.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2022-05-11
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2024-08-11

This document supersedes EN 61936-1:2010 and all of its amendments and corrigenda (if any).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

Any feedback and questions on this document should be directed to the users' national committee. A complete listing of these bodies can be found on the CENELEC website.

Endorsement notice

The text of the International Standard IEC 61936-1:2021 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60034-3	NOTE	Harmonized as EN IEC 60034-3
IEC 60038	NOTE	Harmonized as EN 60038
IEC 60068 (series)	NOTE	Harmonized as EN 60068 (series)
IEC 60076-13	NOTE	Harmonized as EN 60076-13
IEC 60092 (series)	NOTE	Harmonized as EN 60092 (series)
IEC 60282-1	NOTE	Harmonized as EN IEC 60282-1
IEC 60364-4-41	NOTE	Harmonized as HD 60364-4-41
IEC 60364-7-729	NOTE	Harmonized as HD 60364-7-729
IEC 60376	NOTE	Harmonized as EN IEC 60376
IEC 60480	NOTE	Harmonized as EN IEC 60480
IEC 60664-1	NOTE	Harmonized as EN IEC 60664-1
IEC 60721 (series)	NOTE	Harmonized as EN 60721 (series)
IEC 60721-2-2	NOTE	Harmonized as EN 60721-2-2

IEC 60721-2-3	NOTE	Harmonized as EN 60721-2-3
IEC 60721-2-4	NOTE	Harmonized as EN IEC 60721-2-4
IEC 60721-2-7	NOTE	Harmonized as EN IEC 60721-2-7
IEC 60721-3-1	NOTE	Harmonized as EN IEC 60721-3-1
IEC 60721-3-2	NOTE	Harmonized as EN IEC 60721-3-2
IEC 60832 (series)	NOTE	Harmonized as EN 60832 (series)
IEC 60855-1	NOTE	Harmonized as EN 60855-1
IEC 60865-1	NOTE	Harmonized as EN 60865-1
IEC 60909 (series)	NOTE	Harmonized as EN 60909 (series)
IEC 61000 (series)	NOTE	Harmonized as EN IEC 61000 (series)
IEC 61039	NOTE	Harmonized as EN 61039
IEC 61082-1	NOTE	Harmonized as EN 61082-1
IEC 61243 (series)	NOTE	Harmonized as EN 61243 (series)
IEC 61355-1	NOTE	Harmonized as EN 61355-1
IEC 61869 (series)	NOTE	Harmonized as EN IEC 61869 (series)
IEC 62271-4	NOTE	Harmonized as EN 62271-4
IEC 62271-100	NOTE	Harmonized as EN 62271-100
IEC 62271-102	NOTE	Harmonized as EN IEC 62271-102
IEC 62271-103	NOTE	Harmonized as EN 62271-103
IEC 62271-104	NOTE	Harmonized as EN IEC 62271-104
IEC 62271-105	NOTE	Harmonized as EN 62271-105
IEC 62271-206	NOTE	Harmonized as EN 62271-206
IEC 62305 (series)	NOTE	Harmonized as EN 62305 (series)
IEC 81346 (series)	NOTE	Harmonized as EN IEC 81346 (series)
ISO 26800	NOTE	Harmonized as EN ISO 26800

A11 Amendment A11 European foreword

This document (EN IEC 61936-1:2021/A11:2025) has been prepared by CLC/TC 99X "Power installations exceeding 1 kV a.c. (1,5 kV d.c.)".

The following dates are fixed:

- latest date by which this document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2026-12-31
- latest date by which the national standards conflicting with this document have to be withdrawn (dow) 2028-12-31

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

Any feedback and questions on this document should be directed to the users' national committee. A complete listing of these bodies can be found on the CENELEC website. **A11**

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Power installations exceeding 1 kV AC and 1,5 kV DC –
Part 1: AC**

**Installations électriques de puissance de tension supérieure à 1 kV en courant
alternatif et 1,5 kV en courant continu –
Partie 1: Courant alternatif**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2021 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC online collection - oc.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 18 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC - webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études, ...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

IEC online collection - oc.iec.ch

Découvrez notre puissant moteur de recherche et consultez gratuitement tous les aperçus des publications. Avec un abonnement, vous aurez toujours accès à un contenu à jour adapté à vos besoins.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Power installations exceeding 1 kV AC and 1,5 kV DC –
Part 1: AC**

**Installations électriques de puissance de tension supérieure à 1 kV en courant
alternatif et 1,5 kV en courant continu –
Partie 1: Courant alternatif**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.020; 29.080.01

ISBN 978-2-8322-9887-9

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	11
1 Scope.....	12
2 Normative references.....	13
3 Terms and definitions	15
3.1 General definitions	15
3.2 Definitions concerning electrical power installations	17
3.3 Definitions concerning types of electrical power installations	18
3.4 Definitions concerning safety measures against electric shock	18
3.5 Definitions concerning clearances	19
3.6 Definitions concerning control and protection	21
3.7 Definitions concerning earthing.....	21
4 Fundamental requirements.....	25
4.1 General.....	25
4.1.1 General requirements.....	25
4.1.2 Agreements between supplier and user	26
4.2 Electrical requirements.....	28
4.2.1 Methods of neutral earthing.....	28
4.2.2 Voltage classification	28
4.2.3 Current in normal operation.....	28
4.2.4 Short-circuit current	28
4.2.5 Rated frequency.....	29
4.2.6 Corona	29
4.2.7 Electric and magnetic fields.....	29
4.2.8 Overvoltages	30
4.2.9 Harmonics	30
4.2.10 Electromagnetic compatibility	30
4.3 Mechanical requirements.....	30
4.3.1 General	30
4.3.2 Tension load	31
4.3.3 Erection load.....	31
4.3.4 Ice load	31
4.3.5 Wind load	31
4.3.6 Switching forces.....	31
4.3.7 Short-circuit forces.....	31
4.3.8 Loss of conductor tension	31
4.3.9 Seismic loads	31
4.3.10 Dimensioning of structures	32
4.4 Climatic and environmental conditions	32
4.4.1 General	32
4.4.2 Normal conditions	32
4.4.3 Special conditions	34
4.5 Particular requirements	35
4.5.1 Effects of small animals and micro-organisms.....	35
4.5.2 Noise level.....	35

4.5.3	Transport.....	35
5	Insulation	35
5.1	General.....	35
5.2	Selection of insulation level	36
5.2.1	General	36
5.2.2	Consideration of methods of neutral earthing	36
5.2.3	Consideration of rated withstand voltages.....	36
5.3	Verification of withstand values	36
5.4	Minimum clearances of live parts.....	37
5.4.1	General	37
5.4.2	Minimum clearances in voltage range I	37
5.4.3	Minimum clearances in voltage range II	37
5.5	Minimum clearances between parts under special conditions	40
5.6	Tested connection zones.....	40
6	Electrical equipment	40
6.1	General requirements.....	40
6.1.1	Electrical equipment safety.....	40
6.1.2	User safety	41
6.2	Specific requirements.....	41
6.2.1	Switching devices	41
6.2.2	Power transformers and reactors.....	42
6.2.3	Prefabricated type-tested switchgear.....	42
6.2.4	Instrument transformers	42
6.2.5	Surge arresters	43
6.2.6	Capacitors	43
6.2.7	Line traps	44
6.2.8	Insulators.....	44
6.2.9	Insulated cables.....	44
6.2.10	Conductors and accessories.....	47
6.2.11	Rotating electrical machines.....	47
6.2.12	Generating units	48
6.2.13	Generating unit main connections.....	48
6.2.14	Static converters	48
6.2.15	Fuses	49
6.2.16	Electrical and mechanical interlocking	49
7	Electrical power installations.....	49
7.1	General.....	49
7.1.1	Common requirements	49
7.1.2	Circuit arrangement	50
7.1.3	Documentation.....	51
7.1.4	Transport routes	51
7.1.5	Aisles and access areas.....	52
7.1.6	Lighting	53
7.1.7	Operational safety.....	53
7.1.8	Labelling.....	53
7.2	Outdoor electrical power installations of open design	53
7.2.1	General	53
7.2.2	Protective barrier clearances	54

7.2.3	Protective obstacle clearances	54
7.2.4	Boundary clearances.....	55
7.2.5	Minimum height over access area.....	56
7.2.6	Clearances to buildings	57
7.2.7	External fences or walls and access doors.....	59
7.3	Indoor electrical power installations of open design.....	59
7.4	Installation of prefabricated type-tested switchgear	60
7.4.1	General	60
7.4.2	Additional requirements for gas-insulated metal-enclosed switchgear.....	60
7.5	Requirements for buildings	62
7.5.1	General	62
7.5.2	Structural provisions	62
7.5.3	Rooms for switchgear.....	63
7.5.4	Maintenance and operating areas	63
7.5.5	Doors	63
7.5.6	Draining of insulating liquids.....	64
7.5.7	Heating, ventilation and air conditioning (HVAC).....	64
7.5.8	Buildings which require special consideration	65
7.6	High voltage/low voltage prefabricated substations	65
7.7	Electrical power installations on mast, pole and tower	65
8	Safety measures.....	66
8.1	General.....	66
8.2	Protection against direct contact.....	66
8.2.1	General	66
8.2.2	Measures for protection against direct contact	66
8.2.3	Protection requirements	67
8.3	Means to protect persons in case of indirect contact	68
8.4	Means to protect persons working on or near electrical power installations	68
8.4.1	General	68
8.4.2	Electrical equipment for isolating installations or apparatus	68
8.4.3	Devices to prevent reclosing of isolating devices	69
8.4.4	Devices for determining the de-energized state.....	69
8.4.5	Devices for earthing and short-circuiting	69
8.4.6	Equipment acting as protective barriers against adjacent live parts	70
8.4.7	Storage of personal protection equipment.....	71
8.5	Protection from danger resulting from arc fault.....	71
8.6	Protection against direct lightning strokes	72
8.7	Protection against fire	72
8.7.1	General	72
8.7.2	Transformers, reactors	73
8.7.3	Cables	80
8.7.4	Other equipment with flammable liquid	80
8.8	Protection against leakage of insulating liquid and SF ₆	81
8.8.1	Insulating liquid leakage and subsoil water protection	81
8.8.2	SF ₆ leakage	84
8.8.3	Failure with loss of SF ₆ and its decomposition products.....	85
8.9	Identification and marking.....	85
8.9.1	General	85

8.9.2	Information plates and warning plates.....	85
8.9.3	Electrical hazard warning	85
8.9.4	Electrical power installations with incorporated capacitors.....	85
8.9.5	Emergency signs for emergency exits.....	86
8.9.6	Cable identification marks	86
9	Protection, automation and auxiliary systems	86
9.1	Protection systems.....	86
9.2	Automation systems	86
9.3	Auxiliary systems	88
9.3.1	AC and DC supply circuits.....	88
9.3.2	Compressed air systems	89
9.3.3	SF ₆ gas handling plants.....	90
9.3.4	Hydrogen handling plants.....	90
9.4	Basic rules for electromagnetic compatibility of control systems	90
9.4.1	General	90
9.4.2	Electrical noise sources in electrical power installations.....	90
9.4.3	Measures to be taken to reduce the effects of high frequency interference	91
9.4.4	Measures to be taken to reduce the effects of low frequency interference	91
9.4.5	Measures related to the selection of electrical equipment.....	92
9.4.6	Other possible measures to reduce the effects of interference.....	92
10	Earthing systems.....	92
10.1	General.....	92
10.2	Fundamental requirements	93
10.2.1	Safety criteria	93
10.2.2	Functional requirements	93
10.2.3	High and low voltage earthing systems	94
10.3	Design of earthing systems	95
10.3.1	General	95
10.3.2	Power system faults	96
10.3.3	Lightning and transient overvoltages	96
10.4	Construction work on earthing systems	96
10.5	Measurements	97
10.6	Maintainability.....	97
10.6.1	Inspections	97
10.6.2	Measurements	97
11	Inspection and testing.....	98
11.1	General.....	98
11.2	Verification of specified performances	98
11.3	Tests during installation and commissioning	99
11.4	Trial running.....	99
12	Operation and maintenance manual	99
Annex A (informative) Values of rated insulation levels and minimum clearances based on current practice in some countries.....		100
Annex B (normative) Method of calculating permissible touch voltages		103
Annex C (A11) informative (A11) Permissible touch voltage according to IEEE 80		104
Annex D (A11) informative (A11) Earthing system design flow chart.....		105

Annex E (informative) Protection measures against direct lightning strokes	106
E.1 General.....	106
E.2 Shield wires	106
E.3 Lightning rods	106
Annex F (informative) Considerations of design for safe working.....	109
Annex ZA (normative) Normative references to international publications with their corresponding European publications	112
▣ ^{A11} Annex ZA (normative) Special national conditions ▣ ^{A11}	115
▣ ^{A11} Annex ZB (informative) A-deviations ▣ ^{A11}	117
Bibliography	127
Figure 1 – Minimum approach distance for transport within closed electrical operating areas.....	52
Figure 2 – Protection against direct contact by protective barriers or protective obstacles within closed electrical operating areas	55
Figure 3 – Boundary distances and minimum height at the external fence/wall	56
Figure 4 – Minimum heights within closed electrical operating areas	57
Figure 5 – Approaches with buildings within closed electrical operating areas	58
Figure 6 – Separating walls between transformers	76
Figure 7 – Fire protection between transformer and building	78
Figure 8 – Example for small transformers without gravel layer and catchment tank	81
Figure 9 – Sump with integrated catchment tank.....	83
Figure 10 – Sump with separate catchment tank.....	83
Figure 11 – Sump with integrated common catchment tank	84
Figure 12 – Permissible touch voltage U_{Tp}	97
Figure C.1 – Permissible touch voltage U_{Tp} according to IEEE 80	104
Figure E.1 – Single shield wire	107
Figure E.2 – Two shield wires	107
Figure E.3 – Single lightning rod	108
Figure E.4 – Two lightning rods.....	108
Figure F.1 – Working clearances within closed electrical operating areas	110
Table 1 – References to subclauses where agreement between supplier and user is required.....	27
Table 2 – Minimum clearances in air – Voltage range I ($1 \text{ kV} < U_m \leq 245 \text{ kV}$).....	38
Table 3 – Minimum clearances in air – Voltage range II ($U_m > 245 \text{ kV}$)	39
Table 4 – Guide values for outdoor transformer clearances	75
Table 5 – Minimum requirements for the installation of indoor transformers	79
Table 6 – Minimum requirements for interconnection of low-voltage and high-voltage earthing systems based on EPR limits.....	95
Table A.1 – Values of rated insulation levels and minimum clearances in air for $1 \text{ kV} < U_m \leq 245 \text{ kV}$ for highest voltage for installation U_m not standardized by the IEC based on current practice in some countries	100

Table A.2 – Values of rated insulation levels and minimum clearances in air for
 $1 \text{ kV} < U_m \leq 245 \text{ kV}$ for highest voltage for installation U_m not standardized by the IEC
based on current practice in some countries 101

Table A.3 – Values of rated insulation levels and minimum clearances in air for
 $U_m > 245 \text{ kV}$ for highest voltages for installation U_m not standardized by the IEC
based on current practice in some countries 102

This document is a preview generated by EVS

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**POWER INSTALLATIONS EXCEEDING
1 kV AC AND 1,5 kV DC –****Part 1: AC****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61936-1 has been prepared by IEC technical committee 99: Insulation co-ordination and system engineering of high voltage electrical power installations above 1,0 kV AC and 1,5 kV DC.

This third edition cancels and replaces the second edition published in 2010 and Amendment 1:2014. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) introduction has been rewritten to reflect the status when this document is produced;
- b) the scope has been improved to clarify the application of this document;
- c) missing and obsolete terms and definitions have been updated including improvement of existing terms;
- d) Table 1 has been updated where agreements between supplier and user are needed;
- e) requirements of electromagnetic compatibility have been clarified;

- f) insulation coordination clause (Clause 5) has improved wording for better clarity and the technical content has an updated coordination to the latest versions of the insulation coordination standards;
- g) wording regarding electrical equipment has been improved and made clearer;
- h) subclause for fuses has been improved and reworded;
- i) requirements have been added for labelling when multiple sources are required to be disconnected;
- j) missing requirements for GIS have been reintroduced;
- k) subclause regarding ventilation (HVAC) has been improved;
- l) figures in Clause 7 have been updated and moved to the corresponding subclause;
- m) requirements for transformer installations have been improved including adjustment of editorial typing-errors;
- n) clause on protection, automation and auxiliary systems has been restructured and improved;
- o) protection against lightning strokes has been extended;
- p) clarification of content due to the distinction between erection (and providing electrical safety for the intended use of the electrical power installation) and subsequent activities such as maintenance and repair with safe working procedures;
- q) where no provincial, national or regional regulations are available for safe working procedures, an informative guideline is provided in Annex F. This replaces the former parts of Figure 3 in Clause 7.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
99/311/FDIS	99/316/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61936 series, published under the general title *Power installations exceeding 1 kV AC and 1,5 kV DC*, can be found on the IEC website.

A document on principles to be observed in the preparation of safety publications regarding high voltage installations is currently under development (IEC TS 61936-0).

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

The reader's attention is drawn to the fact that **Tõrge! Ei leia viiteallikat.** lists all of the "in-some-country" clauses on differing practices of a less permanent nature relating to the subject of this document.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

This document is a preview generated by EVS

INTRODUCTION

This part of IEC 61936 contains the minimum requirements for the design, erection, and verification of high voltage power installations greater than 1 kV AC. The rules are intended to provide for the safety of persons, livestock and property against dangers and damage which may arise in the reasonable use of such electrical installations and to provide for the proper functioning of those installations.

There are many provincial, national and regional laws, standards and internal rules dealing with the matter coming within the scope of this document regarding high voltage power installations. These practices have been taken as a basis for this work.

This third edition of IEC 61936-1, first published in 2001, follows worldwide feedback to improve clarity. It continues the effort to towards the alignment all over the world of practices concerning the design and erection of high voltage power installations.

Particular requirements for transmission and distribution installations, as well as particular requirements for power generation and industrial installations, are included in this document.

While national standards and regulations take precedence, jurisdictions may elect to adopt the requirements of this document.

© EVS is a preview generated by EVS

POWER INSTALLATIONS EXCEEDING 1 kV AC AND 1,5 kV DC –

Part 1: AC

1 Scope

This part of IEC 61936 provides requirements for the design and the erection of electrical power installations in systems with nominal voltages exceeding 1 kV AC and nominal frequency up to and including 60 Hz, so as to provide safety and proper functioning for the use intended.

For the purpose of interpreting this document, an electrical power installation is considered to be one of the following:

- a) substation, including substation for railway power supply;
- b) electrical power installations on mast, pole and tower, switchgear and/or transformers located outside a closed electrical operating area;
- c) one (or more) power station(s) located on a single site, the electrical power installation includes generators and transformers with all associated switchgear and all electrical auxiliary systems. Connections between generating stations located on different sites are excluded;
- d) the electrical system of a factory, industrial plant or other industrial, agricultural, commercial or public premises;
- e) electrical power installations on offshore facilities for the purpose of generation, transmission, distribution and/or storage of electricity;
- f) transition towers/poles (between overhead lines and underground lines).

The electrical power installation includes, among others, the following equipment:

- rotating electrical machines;
- switchgear;
- transformers and reactors;
- converters;
- cables;
- wiring systems;
- batteries;
- capacitors;
- earthing systems;
- buildings and fences which are part of a closed electrical operating area;
- associated protection, control and auxiliary systems;
- large air core reactor.

NOTE 1 In general, equipment standards take precedence over the requirements of this document.

This document does not apply to the design and erection of any of the following:

- overhead and underground lines between separate electrical power installations;
- electrified railway tracks and rolling stock;
- mining equipment and installations;

- fluorescent lamp installations;
- installations on ships according to IEC 60092 (all parts) and offshore units according to IEC 61892 (all parts), which are used in the offshore petroleum industry for drilling, processing and storage purposes;
- electrostatic equipment (e.g. electrostatic precipitators, spray-painting units);
- test sites;
- medical equipment, e.g. medical X-ray equipment.

This document does not apply to the design of prefabricated, type-tested switchgear and high voltage/low voltage prefabricated substation, for which separate IEC standards exist.

NOTE 2 The scope of this document does not include the requirements for carrying out live working on electrical power installations.

NOTE 3 The scope of this document considers safety requirements for HV installations and the influences of HV installations on LV installations. For electrical installations up to 1 kV, IEC 60364 (all parts) applies.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-1, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60060-1, *High-voltage test techniques – Part 1: General definitions and test requirements*

IEC 60071-1:2019, *Insulation co-ordination – Part 1: Definitions, principles and rules*

IEC 60071-2, *Insulation co-ordination – Part 2: Application guidelines*

IEC 60076 (all parts), *Power transformers*

IEC 60079-0, *Explosive atmospheres – Part 0: Equipment – General requirements*

IEC 60079-10-1, *Explosive atmospheres – Part 10-1: Classification of areas – Explosive gas atmospheres*

IEC 60079-10-2, *Explosive atmospheres – Part 10-2: Classification of areas – Explosive dust atmospheres*

IEC 60255 (all parts), *Measuring relays and protection equipment*

IEC 60331-1, *Tests for electric cables under fire conditions – Circuit integrity – Part 1: Test method for fire with shock at a temperature of at least 830 °C for cables of rated voltage up to and including 0,6/1,0 kV and with an overall diameter exceeding 20 mm*

IEC 60331-21, *Tests for electric cables under fire conditions – Circuit integrity – Part 21: Procedures and requirements – Cables of rated voltage up to and including 0,6/1,0 kV*

IEC 60332 (all parts), *Tests on electric and optical fibre cables under fire conditions*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60479-1:2018, *Effects of current on human beings and livestock – Part 1: General aspects*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60754 (all parts), *Test on gases evolved during combustion of materials from cables*

IEC TS 60815-1, *Selection and dimensioning of high-voltage insulators intended for use in polluted conditions – Part 1: Definitions, information and general principles*

IEC TS 60815-2, *Selection and dimensioning of high-voltage insulators intended for use in polluted conditions – Part 2: Ceramic and glass insulators for a.c. systems*

IEC TS 60815-3, *Selection and dimensioning of high-voltage insulators intended for use in polluted conditions – Part 3: Polymer insulators for a.c. systems*

IEC TR 61000-5-2, *Electromagnetic compatibility (EMC) – Part 5: Installation and mitigation guidelines – Section 2: Earthing and cabling*

IEC 61034-1, *Measurement of smoke density of cables burning under defined conditions – Part 1: Test apparatus*

IEC 61219, *Live working – Earthing or earthing and short-circuiting equipment using lances as a short-circuiting device – Lance earthing*

IEC 61230, *Live working – Portable equipment for earthing or earthing and short-circuiting*

IEC TS 61463, *Bushings – Seismic qualification*

IEC 62271-1:2017, *High-voltage switchgear and controlgear – Part 1: Common specifications for alternating current switchgear and controlgear*

IEC 62271-200, *High-voltage switchgear and controlgear – Part 200: AC metal-enclosed switchgear and controlgear for rated voltages above 1 kV and up to and including 52 kV*

IEC 62271-201, *High-voltage switchgear and controlgear – Part 201: AC solid-insulation enclosed switchgear and controlgear for rated voltages above 1 kV and up to and including 52 kV*

IEC 62271-202, *High-voltage switchgear and controlgear – Part 202: High-voltage/low-voltage prefabricated substation*

IEC 62271-203, *High-voltage switchgear and controlgear – Part 203: Gas-insulated metal-enclosed switchgear for rated voltages above 52 kV*

IEC 62271-207, *High-voltage switchgear and controlgear – Part 207: Seismic qualification for gas-insulated switchgear assemblies for rated voltages above 52 kV*

IEC TR 62271-300, *High-voltage switchgear and controlgear – Part 300: Seismic qualification of alternating current circuit-breakers*

IEC 62305 (all parts), *Protection against lightning*

IEC/IEEE 82079-1, *Preparation of information for use (instructions for use) of products – Part 1: Principles and general requirements*

EN 50522, *Earthing of power installations exceeding 1 kV a.c.*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1 General definitions

3.1.1

electrical equipment

item used for such purposes as generation, conversion, transmission, distribution or utilization of electric energy, such as electric machines, transformers, switchgear and controlgear, measuring instruments, protective devices, wiring systems, current-using equipment

[SOURCE: IEC 60050-826:2004, 826-16-01, modified – In the term, "electric" has been replaced by "electrical".]

3.1.2

nominal value

value of a quantity used to designate and identify a component, device, equipment or system

[SOURCE: IEC 60050-151:2001, 151-16-09, modified – The note has been removed.]

3.1.3

rated value

value of a quantity used for specification purposes, established for a specified set of operating conditions of a component, device, equipment, or system

[SOURCE: IEC 60050-151:2001, 151-16-08]

3.1.4

highest voltage for installation

U_m

highest RMS value of phase-to-phase voltage for which the installation is designed in respect of its insulation

Note 1 to entry: For the purpose of this document, "highest voltage for installation U_m " is equal to "highest voltage for equipment U_m " according to IEC 60071-1.

3.1.5

tested connection zone

zone in the vicinity of equipment terminals which has passed a dielectric type test with the appropriate withstand value(s), the applicable conductors being connected to the terminals in a manner specified by the manufacturer of the equipment

3.1.6

isolating distance

<of a pole of a mechanical switching device> clearance between open contacts meeting the safety requirements specified for disconnectors

[SOURCE: IEC 60050-441:2000, 441-17-35]